Panasonic

Operating Instructions

Digital Cordless Phone with Answering Machine and Link2Cell Feature

Model No. KX-TGF372C KX-TGF373C KX-TG175CSK



Model shown is KX-TG175SK.

Before initial use, see "Getting Started" on page 10.

Thank you for purchasing a Panasonic product.

Please read these operating instructions before using the unit and save them for future reference.

For assistance, please visit our Support page:

www.panasonic.ca/english/support

Table of Contents

Introduction Model composition 3 Accessory information 3 Graphical symbols for use on equipment and their descriptions 5 Important Information 5 For your safety 6 Important safety instructions 7 For best performance 7 Other information 8 Specifications 9	Phonebook Speed dial Programm Menu list Alarm Night mode Baby monitor Other prograi Registering a
Getting Started Setting up	Call Displ Using Call Di Caller list
Display icons/Indicators13Language settings15Date and time15Recording your greeting message15Other settings15	Using Blu Copying phoi (phonebook t Link to Cell a Text messag Alert settings
Link to Cell Link to cell feature	Using a Bluer for landline co
Making/Answering Calls Usingthe HandsetMaking cellular calls.20Making landline calls.20Answering calls.21Useful features during a call.21Power backup operation for landline.24	Turning the a Greeting mes Listening to n Advanced ne features Remote oper Answering sy
Making/Answering Calls Using the Base Unit Making cellular calls	Useful Inf Voicemail sei Wall mountin Error messag Troubleshoot Innovation, S Development
Intercom Intercom30	information Warranty
Call Block Using the [CALL BLOCK] button31 Storing unwanted callers31	Index Index

Phonebook	
Phonebook	34
Speed dial	37
Programming	
Menu list	30
Alarm	
Night mode	
Baby monitor	
Other programming	
Registering a unit	
Call Display Service	
Jsing Call Display service	53
Caller list	
Using Bluetooth® Devices	
Copying phonebook from a cellular phone	
phonebook transfer)	
ink to Cell app	
Text message (SMS) alert	
Alert settings for your DECT phone	
Jsing a Bluetooth wireless headset (option	nal)
or landline calls	60
Answering System for Landlin	е
Answering system for landline	62
Furning the answering system on/off	
Greeting message	62
istening to messages	
Advanced new message alerting	
eatures	65
Remote operation	66
Answering system settings	
Useful Information	
Voicemail service for landline	60
Wall mounting	
Error messages	
Froubleshooting	
	/3
nnovation, Science and Economic	
Development Canada Notices and other	0.4
nformation	
Narranty	82
ndex	

Model composition


Series	Model No.	Base unit Handset	Handset	
Series	woder No.	Part No.	Part No. Quant	
KX-TGF370 series	KX-TGF372	KX-TGF370	KX-TGFA30	2
	KX-TGF373	KX-TGF370	KX-TGFA30	3
	KX-TG175SK	KX-TGF370	KX-TGFA30	5

Accessory information

Supplied accessories

No.	Accessory item/Part number	Quantity		
No. Accessory item/Part number	KX-TGF372	KX-TGF373	KX-TG175SK	
1	AC adaptor/PNLV226	1	1	1
2	Telephone line cord	1	1	1
3	Desk stand/Wall mounting adaptor*1	1	1	1
4	Rechargeable batteries*2	4	6	10
(5)	Handset cover*3	2	3	5
6	Belt clip	2	3	5
7	Charger	1	2	4

- *1 The desk stand/wall mounting adaptor comes attached to the base unit.
- *2 See page 4 for replacement battery information.
- *3 The handset cover comes attached to the handset.



Additional/replacement accessories

Please contact your nearest Panasonic dealer for sales information.

Introduction

Accessory item	Model number/Specifications
Rechargeable	HHR-4DPA*1
batteries	Battery type: - Nickel metal hydride (Ni-MH) - 2 x AAA (R03) size for each handset
Headset	KX-TCA60, KX-TCA93, KX-TCA400, KX-TCA430
Key detector	KX-TGA20*2

- *1 Replacement batteries may have a different capacity from that of the supplied batteries.
- *2 By registering the key detector (4 max.) to a Panasonic Digital Cordless Phone and attaching it to an easy-to-lose item in advance, you can locate and find the mislaid item to which the key detector is attached. Please visit our Web site: www.panasonic.net/pcc/products/telephone/p/tga20/

Other information

- Design and specifications are subject to change without notice.
- The illustrations in these instructions may vary slightly from the actual product.

Expanding your phone system

Handset (optional): KX-TGFA30C	
You can expand your phone system by registering optional handsets (6 max.) to a single base unit. Optional handsets may be a different colour from that of the supplied handsets.	

Bluetooth® devices

You can expand your phone system by pairing the following units to a single base unit.

Your Bluetooth cellular phone*1: 2 max. (for cellular calls: page 16)	
Your Bluetooth headset*1: 1 max. (for a wireless hands-free conversation: page 60)	

- *1 Your cellular phone and headset must be Bluetooth wireless technology compatible. For more details and the list of compatible cellular phones, please visit our Web site: www.panasonic.ca/link2cell
- For assistance, visit www.panasonic.ca/english/support 4

Trademarks

- The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc., and any use of such marks by Panasonic Corporation is under licence.
- iPhone is a trademark of Apple Inc., registered in the U.S. and other countries.
- Android is a trademark of Google Inc.
- Gmail, Google Calendar are trademarks of Google Inc.
- Facebook is trademark of Facebook, Inc.
- Twitter is trademark of Twitter Inc.
- Instagram is trademark of Instagram, Inc.
- BlackBerry is owned by Research In Motion Limited and is registered in the United States and may be pending or registered in other countries. Panasonic is not endorsed, sponsored, affiliated with or otherwise authorized by Research In Motion Limited.
- All other trademarks identified herein are the property of their respective owners.

Graphical symbols for use on equipment and their descriptions

Symbol	Explanation	Symbol	Explanation
\sim	Alternating current (A.C.)		Class II equipment (equipment in which protection against electric shock relies on Double Insulation or Reinforced Insulation)
===	Direct current (D.C.)		"ON" (power)
	Protective earth		"OFF" (power)
<u>_</u>	Protective bonding earth	(h	Stand-by (power)
<i></i>	Functional earth		"ON"/"OFF" (power; push-push)
	For indoor use only	<u>/</u>	Caution, risk of electric shock

For your safety

To prevent severe injury and loss of life/ property, read this section carefully before using the product to ensure proper and safe operation of your product.

MARNING

Power connection

- Use only the power source marked on the product.
- Do not overload power outlets and extension cords. This can result in the risk of fire or electric shock.
- Completely insert the AC adaptor/power plug into the power outlet. Failure to do so may cause electric shock and/or excessive heat resulting in a fire.
- Regularly remove any dust, etc. from the AC adaptor/power plug by pulling it from the power outlet, then wiping with a dry cloth. Accumulated dust may cause an insulation defect from moisture, etc. resulting in a fire.
- Unplug the product from power outlets if it emits smoke, an abnormal smell, or makes an unusual noise. These conditions can cause fire or electric shock. Confirm that smoke has stopped emitting and contact us by visiting our Support page:

www.panasonic.ca/english/support

- Unplug from power outlets and never touch the inside of the product if its casing has been broken open.
- Never touch the plug with wet hands.
 Danger of electric shock exists.

Installation

- To prevent the risk of fire or electrical shock, do not expose the product to rain or any type of moisture.
- Do not place or use this product near automatically controlled devices such as automatic doors and fire alarms. Radio waves emitted from this product may cause such devices to malfunction resulting in an accident.

 Do not allow the AC adaptor or telephone line cord to be excessively pulled, bent or placed under heavy objects.

Operating safeguards

- Unplug the product from power outlets before cleaning. Do not use liquid or aerosol cleaners.
- Do not disassemble the product.
- Do not spill liquids (detergents, cleansers, etc.) onto the telephone line cord plug, or allow it to become wet at all. This may cause a fire. If the telephone line cord plug becomes wet, immediately pull it from the telephone wall jack, and do not use.

Medical

- Consult the manufacturer of any personal medical devices, such as pacemakers or hearing aids, to determine if they are adequately shielded from external RF (radio frequency) energy. (The product operates in the frequency range of 1.92 GHz to 1.93 GHz, and the RF transmission power is 115 mW (max.).)
- Do not use the product in health care facilities if any regulations posted in the area instruct you not to do so. Hospitals or health care facilities may be using equipment that could be sensitive to external RF energy.

♠ CAUTION

Installation and location

- Never install telephone wiring during an electrical storm.
- Never install telephone line jacks in wet locations unless the jack is specifically designed for wet locations.
- Never touch uninsulated telephone wires or terminals unless the telephone line has been disconnected at the network interface.
- Use caution when installing or modifying telephone lines.
- The AC adaptor is used as the main disconnect device. Ensure that the AC outlet is installed near the product and is easily accessible.

For assistance, visit www.panasonic.ca/english/support

TG175CSK (en) _0324_ver011. pdf

6

- This product is unable to make calls when:
 - the handset batteries need recharging or have failed.
 - there is a power failure.

Battery

- · We recommend using the batteries noted on page 4. USE ONLY rechargeable Ni-MH batteries AAA (R03) size.
- Do not mix old and new batteries.
- Do not open or mutilate the batteries. Released electrolyte from the batteries is corrosive and may cause burns or injury to the eves or skin. The electrolyte is toxic and may be harmful if swallowed.
- Exercise care when handling the batteries. Do not allow conductive materials such as rings, bracelets, or keys to touch the batteries, otherwise a short circuit may cause the batteries and/or the conductive material to overheat and cause burns.
- Charge the batteries provided with or identified for use with this product only, in accordance with the instructions and limitations specified in this manual.
- Only use a compatible base unit (or charger) to charge the batteries. Do not tamper with the base unit (or charger). Failure to follow these instructions may cause the batteries to swell or explode.

Attention:



A nickel metal hydride battery that is recyclable powers the product you have purchased.

Please call 1-800-8-BATTERY (1-800-822-8837) for information on how to recycle this battery.

Important safety instructions

When using your product, basic safety precautions should always be followed to reduce the risk of fire, electric shock, and injury to persons, including the following:

- 1. Do not use this product near water for example, near a bathtub, washbowl. kitchen sink, or laundry tub, in a wet basement or near a swimming pool.
- 2. Avoid using a telephone (other than a cordless type) during an electrical storm. There may be a remote risk of electric shock from lightning.
- 3. Do not use the telephone to report a gas leak in the vicinity of the leak.
- 4. Use only the power cord and batteries indicated in this manual. Do not dispose of batteries in a fire. They may explode. Check with local codes for possible special disposal instructions.

SAVE THESE INSTRUCTIONS

For best performance

Base unit location/avoiding noise

The base unit and other compatible Panasonic units use radio waves to communicate with each other.

- For maximum coverage and noise-free communications, place your base unit:
 - at a convenient, high, and central location with no obstructions between the handset and base unit in an indoor environment.
 - away from electronic appliances such as TVs, radios, personal computers, wireless devices, or other phones.
 - facing away from radio frequency transmitters, such as external antennas of mobile phone cell stations. (Avoid putting the base unit on a bay window or near a window.)
- Coverage and voice quality depends on the local environmental conditions.

• If the reception for a base unit location is not satisfactory, move the base unit to another location for better reception.

Environment

- Keep the product away from electrical noise generating devices, such as fluorescent lamps and motors.
- The product should be kept free from excessive smoke, dust, high temperature. and vibration.
- The product should not be exposed to direct sunlight.
- Do not place heavy objects on top of the product.
- When you leave the product unused for a long period of time, unplug the product from the power outlet.
- The product should be kept away from heat sources such as heaters, kitchen stoves, etc. It should not be placed in rooms where the temperature is less than 0 °C (32 °F) or greater than 40 °C (104 °F). Damp basements should also be avoided.
- The maximum calling distance may be shortened when the product is used in the following places: Near obstacles such as hills, tunnels, underground, near metal objects such as wire fences, etc.
- Operating the product near electrical appliances may cause interference. Move away from the electrical appliances.

Routine care

- Wipe the outer surface of the product with a soft moist cloth.
- Do not use benzine, thinner, or any abrasive powder.

Other information

CAUTION: Risk of explosion if battery is replaced by an incorrect type. Dispose of used batteries according to the instructions.

Notice for product disposal, transfer. or return

• This product can store your private/ confidential information. To protect your privacy/confidentiality, we recommend that vou erase information such as phonebook or caller list entries from the memory before vou dispose of, transfer, or return the product.

Compliance with TIA-1083 standard

Telephone handsets identified with this logo have reduced noise and interference when used with T-Coil equipped hearing aids and cochlear implants.



For assistance, visit www.panasonic.ca/english/support

8

Specifications

• Standard:

DECT 6.0 (Digital Enhanced Cordless Telecommunications 6.0) Bluetooth wireless technology 2.1

• Frequency range:

1.92 GHz to 1.93 GHz (DECT)

2.402 GHz to 2.48 GHz (Bluetooth)

RF transmission power:

115 mW (max.)

Power source:

120 V AC, 60 Hz

Power consumption:

Base unit:

Standby: Approx. 1.2 W Maximum: Approx. 4.5 W

Charger:

Standby: Approx. 0.1 W Maximum: Approx. 1.8 W

Operating conditions:

 $0 \, ^{\circ}\text{C} - 40 \, ^{\circ}\text{C} \, (32 \, ^{\circ}\text{F} - 104 \, ^{\circ}\text{F}), \, 20 \, \% - 80 \, \%$ relative air humidity (dry)

Setting up

Connections


• If you do not connect the telephone line cord and use only cellular lines, set the cellular line only mode to use this unit more conveniently (page 18).

■ Base unit


- (1) Connect the AC adaptor to the unit by pressing the plug firmly.
- Fasten the cord by hooking it.
- 3 Connect the AC adaptor to the power outlet.
- 4 Connect the telephone line cord to the unit, then to the single-line telephone jack (RJ11C) until you hear a click.
- (5) À DSL/ADSL filter (not supplied) is required if you have a DSL/ADSL service.

Note:

 Use only the supplied Panasonic AC adaptor PNLV226.




1 Connect the AC adaptor to the power outlet.



Battery installation

- USE ONLY rechargeable Ni-MH batteries AAA (R03) size (A).
- Do NOT use alkaline/manganese/Ni-Cd batteries.
- Confirm correct polarities (,).



Follow the directions on the display to set up the unit.

For assistance, visit www.panasonic.ca/english/support

10

Battery charging

Charge for about 7 hours.

- Confirm "Charging" is displayed (A).
- When the batteries are fully charged. "Fully charged" is displayed.



Note when setting up

Note for connections

- The AC adaptor must remain connected at all times. (It is normal for the adaptor to feel warm during use.)
- The AC adaptor should be connected to a vertically oriented or floor-mounted AC outlet. Do not connect the AC adaptor to a ceiling-mounted AC outlet, as the weight of the adaptor may cause it to become disconnected.

Note for battery installation

 Use the supplied rechargeable batteries. For replacement, we recommend using the Panasonic rechargeable batteries noted on page 4, 7.

Note for battery charging

- It is normal for the handset to feel warm during charging.
- Clean the charge contacts of the handset, base unit, and charger with a soft and dry cloth once a month. Before cleaning the unit, disconnect from power outlets and any telephone line cords. Clean more often if

the unit is exposed to grease, dust, or high humidity.

Battery level

Icon	Battery level
	High
	Medium
	Low
\ \\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\	Needs charging.
Ō	Empty

Panasonic Ni-MH battery performance (supplied batteries)

Operation	Operating time
In continuous use	13 hours max.*1
Not in use (standby)	12 days max.*1

*1 If eco mode is on.

Note:

 Actual battery performance depends on usage and ambient environment.


Intelligent eco mode

This feature automatically reduces handset power consumption by suppressing handset transmission power when the handset is close to the base unit.

- When this feature is activated. ECO is displayed. However, during a cellular call, **ECO** is not displayed even though this feature is activated.
- Eco mode is turned off when the clarity booster is activated (page 22).

Controls

Handset



- Belt clip holes
- 2 Speaker
- **③** [**↑**] (TALK)
- 4 Headset jack
- Dial keypad (★: TONE)
- **⑤** 【♣】(SP-PHONE: Speakerphone)
- Microphone
- Receiver
- O Display
- (OFF)
- (FLASH) [CALL WAIT]
- (CALL BLOCK)
- Charge contacts


■ Control type

(A) Soft keys

By pressing a soft key, you can select the feature shown directly above it on the display. After a cellular phone is paired, [CELL] is displayed.

- Navigator key
- [▲], [▼], [◄], or [►]: Scroll through various lists and items.
- VOL. (Volume: [▲] or [▼]): Adjust the receiver or speaker volume while talking.
- 【◀】□□: View the phonebook entry.
- [▶] REDIAL: View the redial list.
- (▼) CID (Call Display): View the caller list.

Base unit



- Charge contacts
- Speaker
- O Display
- (HOLD)
- [REDIAL] [PAUSE]
- (FLASH) [CALL WAIT]
- [SP-PHONE: Speakerphone)

SP-PHONE indicator

[ERASE]

[ANSWER ON/OFF]

ANSWER ON/OFF indicator

- (LOCATOR) [INTERCOM]
 - You can locate a misplaced handset by pressing [LOCATOR].

[EXIT]

- [►■] (PLAY/STOP)
- Message indicator
- (CELL 1) CELL 1 indicator
- (CELL 2)
- **CELL 2 indicator**
- (APP ALERTS)
- Desk stand/Wall mounting adaptor
 - The adaptor is a removable attachment for desk stand or wall mounting use (page 70).
- Microphone
- Dial keypad (★: TONE)
- Control type
 - (A) Soft keys

By pressing a soft key, you can select the feature shown directly above it on the display.

(B) Navigator key

- (▲), (▼), (I◄◄), or (►►I): Scroll through various lists and items.
- VOL. (Volume: [▲] or [▼]): Adjust the speaker volume while talking.
- [I◄]/[►►I]: Repeat/skip messages during playback.

Display icons/Indicators

Handset display items

Item	Meaning
Y	Within base unit range
¥	Out of base unit range
•	The landline is in use. When flashing: The call is put on hold. When flashing rapidly: An incoming call is now being received.

Item	Meaning
□ <u>1</u>	A cellular line is in use.*1 When flashing: The cellular call is put on hold. When flashing rapidly: A cellular call is being received.
ECO	Eco mode is on.*2 (page 11)
% ¹ ₂	A cellular phone is connected.*1 Ready to make/ receive cellular calls. When turned off: A cellular phone is not connected to the base unit. (page 18)
G1 G2	A cellular call is in progress on that line. The cellular line is selected for the setting.
NR	Noise reduction is set. (page 22)
EQ	Equalizer is set. (page 22)
岭	Speakerphone is on. (page 20)
\$ 1	Ringer volume is off.*3 (page 41, 43)
シ	Night mode is on. (page 49)
PRIV.	Privacy mode is on. (page 45)
Ð	Alarm is on. (page 48)
1	Handset number
	Battery level
/→)	Blocked call (page 31)
BOOST	Clarity booster is on.*2 (page 22)
→	Baby monitor is activated. The name/number displayed next to the icon indicates the monitoring unit. (page 49)
In use	Answering system is being used by another handset or the base unit.

Item	Meaning
Cell1 in use	Someone is using the corresponding line.
Cell2 in use	
C1&C2 in use	
Line in use	

- *1 Corresponding lines (1, 2: cellular line) are indicated next to the item.
- *2 During a cellular call, the item is not displayed even though the feature is activated.
- *3 Corresponding lines (1, 2: cellular line, L: landline) are indicated next to the item. If all lines are turned off, no line is indicated.

Base unit display items

Item	Meaning						
Ø ^{C1}	Ringer volume is off.*1 (page 46, 47)						
ジ	Night mode is on. (page 49)						
PRIV.	Privacy mode is on. (page 45)						
GO	"Greeting only" is selected. Caller messages are not recorded. (page 68)						
G1 G2	A cellular call is in progress on that line. The cellular line is selected for the setting.						
APP	App alert is temporarily off. (page 60)						
<i>\</i> ≠3)	Blocked call (page 31)						
*0	A Bluetooth headset is connected to the base unit. It is ready for use.						
Ç	A Bluetooth headset is in use.						
In use	Answering system is being used by the handset.						

Item	Meaning
Cell1 in use	Someone is using the corresponding line.
Cell2 in use	
C1&C2 in use	
Line in use	

Corresponding lines (C1, C2: cellular line, L: landline) are indicated next to the item. If all lines are turned off, no line is indicated.

CELL indicators on the base unit

The CELL indicators show each cellular line status.

Status	Meaning					
On	A cellular phone is connected. Ready to make/receive cellular calls.					
Flashing	 The cellular line is in use. Phonebook entries are being copied from a cellular phone (page 57). The base unit is searching for the paired cellular phone. The base unit is pairing a cellular phone. A cellular call is put on hold. 					
Flashing rapidly	A cellular call is being received.					
Light off	 A cellular phone is not paired to the base unit. A cellular phone is not connected to the base unit (page 18). 					

For assistance, visit www.panasonic.ca/english/support

14

Language settings

Display language

You can select either "English" or "Français" as the display language. The default setting is "English".

Handset / Base unit

- 1 [MENU]#110
- (♠): Select the desired setting. → (SAVE)
- 3 Proceed with the operation for your unit. Handset: [OFF] Base unit: [EXIT]

Voice guidance language

You can select either "English" or "Français" as the voice guidance language of the Talking Call Display and answering system. The default setting is "English".

Handset

- [MENU]#112
- [\$]: Select the desired setting.
- $[SAVE] \rightarrow [OFF]$

Date and time

Handset

- (MENU)#101
- 2 Enter the current month, date, and year by selecting 2 digits for each. **Example:** July 12, 2016 071216
- 3 [OK]
- 4 Enter the current hour and minute (12-hour clock format) by selecting 2 digits for each. Example: 9:30 0930
- 5 ★: Select "AM" or "PM".

$[SAVE] \rightarrow [OFF]$

Note:

 When English is selected as the display language, 12-hour clock format is used. When French is selected, 24-hour clock format is used.

Recording your greeting message

You can record your own greeting message instead of using a pre-recorded greeting message. See page 62 for details.

Handset

- 1 [MENU]#302
- 2 (♠): "Yes" → [SELECT]
- Record a greeting message. → [STOP] \rightarrow [OFF]

Other settings

Dialing mode

If you cannot make calls, change this setting according to your telephone line service. The default setting is "Tone".

"Tone": For tone dial service.

"Pulse": For rotary/pulse dial service.

Handset

- 1 (MENU)#120
- 2 [\$]: Select the desired setting.
- $[SAVE] \rightarrow [OFF]$

Link to Cell

Link to cell feature

You can connect your base unit and cellular phone using Bluetooth wireless technology, so that you can make or answer cellular calls using your phone system. This allows you to:

- use the unit to talk on cellular calls even if some areas of your home have poor cellular reception, simply by placing your cellular phone in an area with good reception.
- talk on cellular calls even if your cellular phone is in your pocket or bag.
- enjoy cordless cellular calls even if your cellular phone plugged in and charging.

Important:

- Your cellular phone must support the Hands Free Profile (HFP) specification.
- You may pair 2 cellular phones and 1 headset.
- The unit can be used to talk on 2 lines at the same time (for example, 2 cellular lines, or the landline and 1 cellular line).
- Only 2 Bluetooth devices can be used with the unit at the same time (for example, 2 cellular lines, or the headset and 1 cellular line).
- Locate your cellular phone near the base unit. If the cellular phone is too close to the base unit during a cellular call, you may hear noise. For best performance, we recommend placing the cellular phone between 0.6 m to 3 m (2 feet to 10 feet) away from the base unit.

Pairing a cellular phone

Important:

- For more details and the list of compatible cellular phones, please visit our Web site: www.panasonic.ca/link2cell
- Before pairing a Bluetooth enabled cellular phone to the base unit, make sure that no other Bluetooth device such as a Bluetooth headset is connected to your cellular phone.

1 Base unit:

16

Press and hold [CELL 1] or [CELL 2] for a few seconds.

 After the corresponding CELL indicator on the base unit starts flashing, the rest of the procedure must be completed within 5 minutes.

2 Your cellular phone:

While the corresponding CELL indicator is flashing, follow the instructions of your cellular phone to enter the pairing mode.

 Depending on your cellular phone, it may ask you to enter the Bluetooth PIN (default: "0000"). If your cellular phone shows PassKey confirmation on its display, follow the directions to proceed.

3 Base unit:

Wait until a long beep sounds.

- It may take more than 10 seconds to complete pairing.
- When the corresponding CELL indicator lights up, the cellular phone is connected to the base unit. You are ready to make cellular calls.

4 [EXIT]

Note:

- Make sure that your cellular phone is set to connect to this product automatically. Refer to your cellular phone's operating instructions.
- Make sure you cancel your cellular phone's current pairing if you want to pair it to the other line (page 16).
- The default setting for the alert feature is "On", so when you pair your cellular phone to the base unit, this feature may be activated (page 59). (This depends on the version and type of cellular phone you are using.)

Unpairing a cellular phone

You can cancel the pairing of a cellular phone that is stored in the base unit.

Handset

1 For CELL 1: [MENU]#6111 For CELL 2: [MENU]#61112

- 2 (♣): "Yes" → [SELECT]
 - When the cellular phone is unpaired, the CELL indicator is turned off.
- 3 [OFF]

Link to cell settings

Selecting which unit receives cellular calls

You can select which unit rings and receives calls for a cellular line. When "All" is selected, all handsets and the base unit ring.

Handset

- 1 For CELL 1: [MENU]#6271 For CELL 2: [MENU]#6272
- 2 [♣]: Select the desired handset or "All".
 → [SAVE]
- 3 [OFF]

Note:

- When you select a specific handset to receive calls for a cellular line:
 - other handsets cannot answer the calls.
 - the base unit can answer the calls even though it does not ring. However, you can make the base unit ring by adjusting the base unit ringer volume (page 46).
- When you change to "All" from another setting, the base unit ringer volume also returns to the lowest level even if the ringer volume was changed.
- The units selected with this setting have the alert feature (page 59) applied to them.

Ring as cell mode

Once this feature is turned on, the handset and base unit ring using the same ringer tone as your cellular phone.

The following settings are available:

 "Off": Turn this feature off to use the ringer tones of the handset and base unit.
 Caller information is announced depending on the Talking Call Display setting (page 43).

- "On (with Talking CID)" (default): The handset and base unit use your cellular phone's ringer tone. Caller information is announced even if the Talking Call Display is turned off.
- "On (without Talking CID)": The handset and base unit use your cellular phone's ringer tone. Caller information is not announced even if the Talking Call Display is turned on.

Important:

 To use this feature, your cellular phone must support Bluetooth in-band ringtone. Refer to your cellular phone's operating instructions.

Handset

- 1 For CELL 1: [MENU]#6141 For CELL 2: [MENU]#6142
- 2 (*): Select the desired setting.
- 3 [SAVE] \rightarrow [OFF]

Note:

- The units use the preset ringer tones instead of your cellular phone's ringer tone when a cellular call is being received if:
 - your cellular phone is in night mode (depending on your cellular phone).
 - the base unit is in use.
 - 2 handsets are sharing a landline call.
- If your cellular phone is in night mode with "On (with Talking CID)" set, the unit announces caller information even when Talking Call Display is turned off (page 43).

To use the handset ringer tone instead of your cellular phone's ringer tone

Select "Off" in step 2, "Ring as cell mode", page 17.

To change the handset ringer tone for a cellular line, see page 41.

Auto connection to the Bluetooth devices (cellular phones)

After pairing, your Bluetooth devices are connected to the base unit. If you move the Bluetooth devices out of base unit range, the Bluetooth devices are disconnected from the base unit. This feature allows the base unit to try to reconnect the Bluetooth devices at regular intervals when it returns within base unit range. You can set the interval. The default setting is "1 min".

Important:

- When 3 Bluetooth devices (2 cellular phones and 1 headset) are paired to the base unit, only 2 Bluetooth devices can be used with the unit at the same time, and the base unit loses its connection from other Bluetooth devices. To automatically resume the connection to Bluetooth devices, leave the auto connection on.
- Some cellular phones lose connection after usage, please check the specifications of your cellular phone for more details.

Handset

- [MENU]#632
- [\$]: Select the desired setting.
- $[SAVE] \rightarrow [OFF]$

Note:

 Some cellular phones may ask you if you accept the connection requirement from the base unit. In that case, select "off" in step 2. Check the specifications of your cellular phone.

Connecting/disconnecting the cellular phone manually

If you will not be using the paired cellular phone's link to cell feature temporarily (for example, you do not want the unit to ring when your cellular line receives a call), you can disconnect your cellular phone from the base unit. If you want to use it again. reconnect the cellular phone to the base unit.

- After vou disconnect a paired cellular phone from the base unit manually, it will automatically be connected to the base unit in 30 minutes. If you do not use the link to cell feature anymore, unpair the cellular phone (page 18).
- A disconnected cellular phone is not unpaired from the base unit, so pairing it to the base unit again is unnecessary.

Handset

To connect/disconnect:

For CELL 1: [MENU]#6251 For CELL 2: [MENU] # 6 2 5 2

- A long beep sounds.
- [OFF]

Cellular line only mode (If you do not use the landline)

If you do not use the landline, we recommend setting the unit to the cellular line only mode. The default setting is "off".

Important:

• If you turn on the "Cell line only mode", disconnect the telephone line cord from the base unit. Otherwise the "Cell line only mode" cannot be activated.

Handset

- 1 (MENU)#157
- To turn on:

 $[\]$: "On" \rightarrow [SELECT] \rightarrow $[\]$: "Yes" → [SELECT]

To turn off:

 $[\ \ \]$: "Off" \rightarrow [SELECT]

Note:

- Once you set this mode, you can use the following buttons to make cellular calls:
 - for the handset, press (♠) instead of [CELL] (page 20).
 - for the base unit, press (♣) without pressing [CELL 1] or [CELL 2] set for the cellular line selection (page 19,
- Once you set this mode, the following features cannot be used:

- Landline features (page 47)
- Answering system (page 62)
 Messages cannot be received.
- Voicemail features (page 69)
- After this mode is turned on or off, the base unit reboots.
 - Bluetooth connections from cellular phones or headset are disconnected. If the auto connection is turned on (page 18), the cellular phones are reconnected.
 - —
 ▼ will be displayed on the handset momentarily. The handset can be used once ▼ is displayed.

When you use the landline again

Before connecting the telephone line to the base unit, select "off" in step 2, "Cellular line only mode (If you do not use the landline)", page 18.

Cellular line selection

This feature determines which cellular line is selected to make cellular calls when:

- you press [CELL] on the handset.
- you press [] or [] on the handset while the cellular line only mode is turned on.
- you press [] on the base unit while the cellular line only mode is turned on.

The following settings are available:

- "Manua1" (handset only: default): You can select the desired cellular line when making a call.
- "Cellphone 1"*1 (base unit default):
 CELL 1 is selected.
- "Cellphone 2"*1: CELL 2 is selected.

Handset / Base unit

- 1 [MENU]#634
- 2 [♣]: Select the desired setting. → [SAVE]
- 3 Proceed with the operation for your unit. Handset: [OFF]

Base unit: [EXIT]

*1 After the Bluetooth device is paired, the device name is displayed.

Storing your area code (for dialing only a 7-digit phone number to make a local call)

You need to add your area code when making cellular calls to a phone number in your area. Once you store your area code, it is automatically added to the beginning of the 7-digit phone number when making cellular

Handset

- 1 [MENU]#633
- 2 Enter the 3-digit area code.
 - To correct a digit, press [CLEAR].
- 3 $[SAVE] \rightarrow [OFF]$

Changing the Bluetooth PIN (Personal Identification Number)

The PIN is used to pair cellular phones to the base unit. The default PIN is "0000". To prevent unauthorized access to this product, we recommend that you change the PIN, and keep it confidential.

Important:

 Please make note of your new PIN. The unit does not reveal the PIN to you. If you forget your PIN, see page 80.

Handset

- 1 (MENU)#6119
 - If the unit prompts you to enter the old PIN (when the default has been changed), enter the current 4-digit PIN.
- 2 Enter the new 4-digit PIN. → [OK]
- 3 Enter the new 4-digit PIN again. → (SAVE)
- 4 [OFF]

Making cellular calls

Important:

- The unit can be used to talk on 2 lines at the same time (for example, 2 cellular lines) or the landline and 1 cellular line).
- Only 2 Bluetooth devices can be used with the unit at the same time (for example, 2) cellular lines, or the headset and 1 cellular line).
- Before making calls, confirm that the corresponding \$\frac{1}{2}\$ on the handset is displayed (page 13).
- Lift the handset and dial the phone
 - To correct a digit, press [CLEAR].

2 [CELL]

- The unit starts dialing when:
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).

Go to step 4.

- 3 (♠): Select the desired cellular phone. → [SELECT]
- When you finish talking, press [OFF] or place the handset on the base unit or charger.

Note:

 To switch to the speaker, press [
]. To switch back to the receiver, press [♣]/ [].

Adjusting the receiver or speaker volume

Press (▲) or (▼) repeatedly while talking.

• The receiver or speaker volume you set is kept for each line (landline and cellular lines).

Making a cellular call using the redial

The last 5 phone numbers dialed are stored in the redial list (each 48 digits max.).

【►】REDIAL

- [\$]: Select the desired phone number.
- [CELL]
 - The unit starts dialing when:
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).
- [♠]: Select the desired cellular phone. → [SELECT]

Erasing a number in the redial list

- When a cellular phone is paired:
 - 【►】REDIAL
 - [\$]: Select the desired phone number. → [MENU]
 - [♠]: "Erase" → [SELECT]
 - [♠]: "Yes" → [SELECT]
 - [OFF]
- When a cellular phone is not paired:
 - 【►】REDIAL
 - [\$]: Select the desired phone number. \rightarrow [ERASE]
 - [♠]: "Yes" → [SELECT]
 - [OFF]

Making landline calls

- Lift the handset and dial the phone number.
 - To correct a digit, press [CLEAR].
- 2
- When you finish talking, press [OFF] or place the handset on the base unit or charger.

Using the speakerphone

- Dial the phone number and press [♣].
- When you finish talking, press [OFF].

Note:

 To switch back to the receiver, press [♣]/

Making a call using the redial list

The last 5 phone numbers dialed are stored in the redial list (each 48 digits max.).

- 【►】REDIAL
- (\$): Select the desired phone number.

Pause (for PBX/long distance service users)

A pause is sometimes required when making calls using a PBX or long distance service. When storing a calling card access number and/or PIN in the phonebook, a pause is also needed (page 37).

Example: If you need to dial the line access number "9" when making outside calls with a PBX:

- $\boxed{9} \rightarrow \boxed{4}$ (Pause)
- Dial the phone number. \rightarrow [\frown]

 A 3.5 second pause is inserted each time [A] (Pause) is pressed.

Answering calls

- Lift the handset and press [] or [] when the unit rings.
 - To answer a cellular call, you can also press [CELL].
- When you finish talking, press [OFF] or place the handset on the base unit or charger.

Any key answer: You can answer the call by pressing any dial key.

Auto talk: You can answer calls simply by lifting the handset (page 44).

Temporary handset ringer off: You can turn the ringer off temporarily by pressing $[\mathcal{A}]$.

Adjusting the handset ringer volume

Press (▲) or (▼) repeatedly to select the desired volume while ringing.

• The ringer volume you set is kept for each line (landline and cellular lines).

Useful features during a call

Hold

- Press [MENU] during an outside call.
- [♣]: "Hold" → [SELECT]
- To release hold on the cellular line: Press [CELL].*1
 - Another handset user can take the call by pressing [CELL].*1
 - If you press [CELL] and the selection list is displayed, select the desired cellular line and press [SELECT].
 - The base unit user can take the call by pressing [CELL 1] or [CELL 2].

To release hold on the landline:

Press [].

- Another handset user can take the call by pressing [>>].
- The base unit user can take the call by pressing [].

Note:

· After holding for 10 minutes, the call is disconnected.

Mute

- Press [MUTE] during a call.
- To return to the call, press (MUTE).

Note:

• [MUTE] is a soft key visible on the display during a call.

Flash for landline calls

(FLASH) allows you to use the special features of your host PBX such as transferring an extension call, or accessing optional telephone services.

Note:

• To change the flash time, see page 45.

For Call Waiting or Visual Call Waiting service users

To use Call Waiting or Visual Call Waiting, you must first subscribe with your phone service provider.

This feature allows you to receive calls while you are already talking on the phone. If you receive a call while on the phone, you will hear a Call Waiting tone.

If you subscribe to both Call Display and Visual Call Waiting services, the 2nd caller's information is displayed after you hear the Call Waiting tone on the handset.

- 1 Press [CALL WAIT] to answer the 2nd call
- 2 To switch between calls, press [CALL WAIT].

Note:

 Please contact your phone service provider for details and availability of this service in your area.

Temporary tone dialing for landline calls (for rotary/pulse service users)

Press ★ (TONE) before entering access numbers which require tone dialing.

Handset clarity booster

This feature can improve sound clarity when the handset is used in an area where there may be interference. During an outside call, this feature is turned on automatically when necessary.

 When this feature is turned on, E00SI is displayed. However, during a cellular call, E00SI is not displayed even though the feature is activated.

Handset noise reduction

This feature allows you to hear the voice of the person you are talking to more clearly, by reducing the surrounding noise coming from the other party's telephone.

- 1 Press [MENU] while talking.
- 2 [♣]: "Noise reduction on" OF
 "Noise reduction off" →
 [SELECT]

Note:

- The setting you made is kept for each line (landline and cellular lines).
 - The default settings are as follows:
 - for landline: "Noise reduction off"
 - for cellular lines: "Noise reduction on"
- Depending on the environment where this handset is being used, this feature may not be effective.
- This feature is not available while using the speakerphone.

Handset equalizer

This feature clarifies the voice of the person you are talking to, producing a more natural-sounding voice that is easier to hear and understand.

- 1 Press [MENU] while talking.
- 2 (♣): "Equalizer" → [SELECT]
- 3 (*): Select the desired setting.
- 4 Press [OK] to exit.

Note:

- The setting you made is kept for each line (landline and cellular lines).
- Depending on the condition and quality of your telephone line, this feature may emphasize existing line noise. If it becomes difficult to hear, turn this feature off.
- This feature is not available while using the speakerphone.
- When both the "Equalizer" setting and noise reduction are activated, NR is shown on the display.

Call share

You can join an existing outside call.

- While another unit is on a cellular call:
 - To join the conversation, press [CELL].
 - You can join the conversation when:
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).
 - [\$]: Select the corresponding cellular phone. \rightarrow [SELECT]
- While another unit is on a landline call: To join the conversation, press [].

Note:

- A maximum of 3 parties (including 1 outside party) can join a conversation using 2 extensions. (3-way conference)
- To prevent other users from joining your conversations with outside callers, turn privacy mode on (page 45).

Transferring calls, conference calls

Outside calls can be transferred or a conference call with an outside party can be made between 2 handsets.

- During an outside call, press [MENU].
- [♠]: "Intercom" → [SELECT]
- 3 (♠): Select the desired unit. → [SELECT]
- 4 Wait for the paged party to answer.
 - If the paged party does not answer. press [BACK] to return to the outside
- To complete the transfer: Press (OFF).

To establish a conference call: $[MENU] \rightarrow [\]$: "Conference" \rightarrow (SELECT)

- To leave the conference, press (OFF). The other 2 parties can continue the conversation.
- To put the outside call on hold: $[MENU] \rightarrow [\ \ \ \]$: "Hold" \rightarrow [SELECT]

To resume the conference: [MENU] → [♣]: "Conference" → [SELECT]

 To cancel the conference: [MENU] → [♣]: "Stop conference" → [SELECT]

You can continue the conversation with the outside caller

Transferring a cellular call between the handset and a cellular phone

Transferring a cellular call from the handset to a cellular phone

- Press [MENU] during a cellular call.
- [♠]: "Transfer to cell" → [SELECT]
 - The cellular call is transferred to the cellular phone.

Note:

Depending on your cellular phone type, you may need to set the cellular phone to be ready to talk before transferring. For example, if your cellular phone has a top cover, open it beforehand.

Transferring a cellular call from a cellular phone to the handset

During a conversation using a cellular phone, the call cannot be transferred to the handset by the cellular phone. Perform the following with the handset.

- During a conversation using a cellular phone, press [CELL].
 - The call is transferred to the handset
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).
- (\$): Select the corresponding cellular phone. \rightarrow [SELECT]
 - The call is transferred to the handset.

Answering a 2nd call

If you receive a call while talking on the phone, the interrupt tone sounds (page 43) and the 2nd caller's information is displayed if you subscribe to Call Display service (page 53).

Answering a 2nd call during a landline call

- Press [MENU] during a landline call.
- 2 [♣]: "Hold" → [SELECT]
- To answer the 2nd call: Press [CELL] while the 2nd call is being received.
- To hang up the 2nd call and return to the 1st call (landline call), press [OFF], then press [>].

Answering a 2nd call during a cellular call

- Press [MENU] during a cellular call.
- [$\ \$]: "Hold" \rightarrow [SELECT]
- To answer the 2nd call: Press [] or [CELL] while the 2nd call is being received.
- To hang up the 2nd call and return to the 1st call (cellular call), press [OFF], then press [CELL].*1
- *1 If you press [CELL] and the selection list is displayed, select the desired cellular line and press [SELECT].

Power backup operation for landline

When a power failure occurs, the charged handset temporarily supplies power to the base unit (power backup mode). This allows you to make and receive landline calls using a handset during a power failure. The base unit will not perform any other functions. However, some functions such as Call Display and phonebook are available only when using a handset other than the handset supplying

power to the base unit. You can program "Power failure" and the default setting is "Auto" (page 45).

Important:

- If a handset is not placed on the base unit when a power failure occurs, "Base no power Press OFF" is displayed. After pressing (OFF) on the handset, place it on the base unit to start power backup mode.
- Power backup mode will not work if the battery level of the power supplying handset is a or .
- Do not lift the power supplying handset from the base unit during power backup mode.

Panasonic Ni-MH battery performance (supplied batteries) during power backup mode

When the batteries are fully charged, operating time of the handset in power backup mode varies depending on usage.

- Continuous use of the handset in power backup mode: 1.5 hours max.
- Continuous use of the handset other than a handset in power backup mode: 2 hours
- Not in use in power backup mode: 2 hours

Making calls during a power failure

- When only 1 handset is registered:
 - Lift the handset and dial the phone number.
 - Within 1 minute, place the handset on the base unit.
 - Wait until speakerphone is turned on automatically and the call is
 - When the other party answers the call, keep the handset on the base unit and talk using the speakerphone.
 - When you finish talking, press [OFF].

For assistance, visit www.panasonic.ca/english/support

24

■ When 2 or more handsets are registered: You should leave one handset on the base unit for supplying the power, and use another handset for making calls.

Note:

 The range of the base unit is limited during a power failure. Please use the handset close to the base unit.

Making a call using the redial list

- When only 1 handset is registered:
 - Lift the handset.
 - 2 [►] REDIAL
 - **3** [♠]: Select the desired phone number.
 - **4** Within 1 minute, place the handset on the base unit.
 - Wait until speakerphone is turned on automatically and the call is made
- When 2 or more handsets are registered: You should leave one handset on the base unit for supplying the power, and use another handset for making calls.

Making a call using the phonebook

There must be at least 2 handsets registered to the base unit in order for the phonebook feature to be used during a power failure.

You should leave one handset on the base unit for supplying the power, and use another handset for making calls.

Answering calls during a power failure

- When only 1 handset is registered:
 - - Speakerphone is turned on.
 - When you finish talking, press [OFF].
- When 2 or more handsets are registered: When the unit rings, use a handset which is not supplying power to the base unit.

 Do not use or lift the handset which is placed on the base unit during power backup mode.

Note:

 The range of the base unit is limited during a power failure. Please use the handset close to the base unit.

Making cellular calls

Important:

- The unit can be used to talk on 2 lines at the same time (for example, 2 cellular lines) or the landline and 1 cellular line).
- Only 2 Bluetooth devices can be used with the unit at the same time (for example, 2) cellular lines, or the headset and 1 cellular line).
- Before making calls, confirm that the corresponding CELL indicator on the base unit lights up (page 14).
- Dial the phone number.
 - To correct a digit, press [CLEAR].
- Press [CELL 1] or [CELL 2].
- When the other party answers, speak into the microphone.
- When you finish talking, press [♣].

Note:

- While on a call, you can switch from the base unit to the handset:
 - With the privacy mode off (page 45). press $[CELL]^{*1}$ on the handset. $\rightarrow [\ \ \ \]$: Select the desired cellular phone. → [SELECT] → Press [♣] on the base unit.
 - If the handset is on the base unit, simply lift it
 - The call is taken when:
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).

Adjusting the speaker volume

Press (▲) or (▼) repeatedly while talking.

Note:

 The speaker volume you set is kept for each line (landline and cellular lines).

Making a cellular call using the redial

The last 10 phone numbers dialed are stored in the redial list (each 48 digits max.).

[REDIAL]

- [\$]: Select the desired phone number.
- Press [CELL 1] or [CELL 2].

Erasing a number in the redial list

- [REDIAL]
- [♣]: Select the desired phone number.
 - → [ERASE]
- $[^{\blacktriangle}_{\blacktriangledown}]$: "Yes" \rightarrow [SELECT]
- [EXIT]

Making landline calls

- Dial the phone number.
 - To correct a digit, press [CLEAR].
- When the other party answers, speak into the microphone.
- When you finish talking, press [♣].

Note:

- While on a call, you can switch from the base unit to the handset:
 - Press () on the handset, then press [on the base unit with the privacy mode off (page 45).
 - If the handset is on the base unit, simply lift it.

Making a call using the redial list

The last 10 phone numbers dialed are stored in the redial list (each 48 digits max.).

- [REDIAL]
- [\$]: Select the desired phone number.
- [4]

Pause (for PBX/long distance service users)

A pause is sometimes required when making calls using a PBX or long distance service. When storing a calling card access number and/or PIN in the phonebook, a pause is also needed (page 37).

Example: If you need to dial the line access number "9" when making outside calls with a PBX:

- 1 $9 \rightarrow [PAUSE]$
- Dial the phone number. \rightarrow [\blacktriangleleft]

Note:

 A 3.5 second pause is inserted each time [PAUSE] is pressed.

Answering calls

- Press [] when the unit rings.
 - You can also answer the cellular call by pressing [CELL 1] or [CELL 2].
- Speak into the microphone.
- When you finish talking, press [♣].

Adjusting the base unit ringer volume

Press (▲) or (▼) repeatedly to select the desired volume while ringing.

Note:

• The ringer volume you set is kept for each line (landline and cellular lines).

Useful features during a call

Hold

- Press [HOLD] during an outside call.
- To release hold on the cellular line: Press [CELL 1] or [CELL 2].
 - A handset user can take the call: $[CELL]^{*1} \rightarrow [\ \ \ \ \]$: Select the corresponding cellular phone. -> [SELECT]
 - The call is taken when:
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).

To release hold on the landline: Press ().

 A handset user can take the call by pressing [>].

Note:

- · While a landline call is on hold, the SP-PHONE indicator flashes.
- After holding for 10 minutes, the call is disconnected.

Mute

- Press [MUTE] during a call.
 - The SP-PHONE indicator flashes.
 - To return to the call, press [MUTE].

Note:

• [MUTE] is a soft key visible on the display during a call.

Flash for landline calls

(FLASH) allows you to use the special features of your host PBX such as transferring an extension call, or accessing optional telephone services.

Note:

To change the flash time, see page 45.

For Call Waiting or Visual Call Waiting service users

To use Call Waiting or Visual Call Waiting, you must first subscribe with your phone service provider.

This feature allows you to receive calls while you are already talking on the phone. If you receive a call while on the phone, you will hear a Call Waiting tone.

If you subscribe to both Call Display and Visual Call Waiting services, the 2nd caller's information is displayed after you hear the Call Waiting tone on the base unit.

- Press [CALL WAIT] to answer the 2nd
- To switch between calls, press [CALL WAIT].

Note:

 Please contact your phone service provider for details and availability of this service in vour area.

Temporary tone dialing for landline calls (for rotary/pulse service users)

Press ★ (TONE) before entering access numbers which require tone dialing.

Call share

You can join an existing outside call. To select the line that is being used for the call: - for a cellular line press [CELL 1] or [CELL 2].

for the landline press (♣).

Noto:

- A maximum of 3 parties (including 1 outside party) can join a conversation using 2 extensions. (3-way conference)
- To prevent other users from joining your conversations with outside callers, turn privacy mode on (page 45).

Transferring calls, conference calls

Outside calls can be transferred or a conference call with an outside party can be made between a handset and the base unit.

During an outside call, press [INTERCOM].

When 2 or more handsets are reaistered:

- To page a specific handset, enter the handset number.
- To page all handsets, press of or wait for a few seconds.
- Wait for the paged party to answer.
 - If paged party does not answer, press [INTERCOM] to return to the outside
- To complete the transfer: Press [].

 The outside call is being routed to the handset

To establish a conference call: Press [CONF].

- To leave the conference, press [♣]. The other 2 parties can continue the conversation.
- To put the outside call on hold, press [HOLD]. To resume the conference, press [CONF].

Transferring a cellular call between the base unit and a cellular phone

Transferring a cellular call from the base unit to a cellular phone

During a cellular call, press and hold [CELL 1) or [CELL 2] until the SP-PHONE indicator goes out.

 The cellular call is transferred to the cellular phone.

Transferring a cellular call from a cellular phone to the base unit

During a conversation using a cellular phone, press [CELL 1] or [CELL 2].

The cellular call is transferred to the base

Answering a 2nd call

If you receive a call while talking on the phone, the interrupt tone sounds (page 47) and the 2nd caller's information is displayed if you subscribe to Call Display service (page 53).

Answering a 2nd call during a landline call

- Press [HOLD] during a landline call.
- To answer the 2nd call: Press [CELL 1] or [CELL 2].
- To hang up the 2nd call and return to the 1st call (landline call), press [♣] 2 times.

Answering a 2nd call during a cellular call

- 1 Press [HOLD] during a cellular call.
- 2 To answer the 2nd call: [♠], [CELL 1], or [CELL 2]
- 3 To hang up the 2nd call and return to the 1st call (cellular call), press [♣], then press [CELL 1] or [CELL 2].

Intercom

Intercom

Intercom calls can be made:

- between handsets
- between a handset and the base unit

Note:

- When paging unit(s), the paged unit(s) beeps for 1 minute.
- If you receive an outside call while talking on the intercom, the interrupt tone sounds (page 43, 47).
 - Handset: To finish intercom, press **(OFF)**. To answer the call, press ().
 - Base unit: To finish intercom, press [♣]. To answer the call, press [♣] again.

Making an intercom call

Handset

- $[MENU] \rightarrow [^{\blacktriangle}]$: "Intercom" \rightarrow [SELECT]
- $[\]$: Select the desired unit. \rightarrow [SELECT]
- When you finish talking, press [OFF].

Note:

 You can also use the [INTERCOM] soft key, if displayed, to make intercom calls.

Base unit

- Press [INTERCOM]. When 2 or more handsets are reaistered:
 - To page a specific handset, enter the handset number.
 - To page all handsets, press or wait for a few seconds.
- When you finish talking, press [♣].

Answering an intercom call

Handset

- Press [] to answer the page.
- When you finish talking, press [OFF].

Base unit

- Press [] to answer the page.
- When you finish talking, press [♣].

Turning auto intercom on/off

This feature allows the handset or base unit to answer intercom calls automatically when it is called. You do not need to press [>>] or []. When this feature is set to "On", the monitoring handset or base unit for the baby monitor feature (page 51) will also answer baby monitor calls automatically. The default setting is "off".

Handset / Base unit

- [MENU]#273
- 2 [♣]: Select the desired setting. → (SAVE)
- Proceed with the operation for your unit Handset: [OFF] Base unit: [EXIT]

For assistance, visit www.panasonic.ca/english/support

TG175CSK (en) _0324_ver011. pdf

30

Using the [CALL BLOCK] button

You can press the [CALL BLOCK] button in the following situations to disconnect the current call and add a phone number to the call block list:

- when an incoming call is being received
- when an incoming call is being recorded by the answering system
- when talking on an outside call

Once a phone number has been added to the call block list, the unit will block calls from that phone number in the future.

Handset

- Press [CALL BLOCK] under the situations shown above.
- 2 Confirm the call block number and press [YES].
 - The call block number is stored in the call block list, "Caller blocked" is displayed, and then the call is disconnected.

Note:

- If the call has no phone number, the call is blocked but it is not stored in the call block list
- The call block feature is not available:
 - for intercom calls or calls received by Call Waiting.
 - when a landline call (or cellular call) is being received during a cellular call (or landline call).
- Blocked calls are logged in the caller list.

Storing unwanted callers

The unit can block calls by storing the desired items in the call block list beforehand (Call Display subscribers only).

- "Block a single number" 1/"Block a single #"'2: The unit blocks calls from specific phone numbers stored in the call block list
- "Block range of numbers"*1/"Block range of #"*2: The unit blocks calls that

begin with a number stored in the call block list, such as a toll-free phone number prefix or certain area codes.

- "Block unknown CID"*1/"Block unknown"*2: The unit blocks calls that have no phone number.
- *1 Handset
- *2 Base unit

Single phone numbers and ranges of numbers can be stored in the call block list up to 250 items in total.

Blocking unwanted callers:

When a call is received, the unit rings briefly¹ while caller information is being received. If the caller's phone number matches an entry in the call block list, the unit emits no sound to the caller, and disconnects the call.

*1 If you do not want this one ring to sound, select "No" in "Setting not to ring once for blocked call" (page 33).

Storing a single phone number

Important:

 We recommend storing 10 digits (including the area code). If only 7 digits are stored, all numbers that have the same last 7 digits will be blocked.

Adding call blocked numbers from the caller list

Handset

- When a cellular phone is paired:
 - 1 [▼] CID
 - 2 (\$): Select the desired entry to be blocked.
 - To edit the number:

[SELECT] → Press ※ (Edit) repeatedly until the phone number is shown in the 10-digit format. → [SAVE] → [\$] "Call block" → [SELECT] → Go to step 4.

- 3 [CALL BLOCK]
- 4 (♦): "Yes" → [SELECT]
- **5** Edit the phone number if necessary (24 digits max.).

Call Block

- 6 [SAVE] → [OFF]
- When a cellular phone is not paired:
 - 1 [V] CID
 - 2 [♣]: Select the desired entry to be blocked.
 - To edit the number: [MENU] →
 [\$]: "Edit" → [SELECT]
 Press [EDIT] repeatedly until the phone number is shown in the 10-digit format. → [SAVE] →
 "Call block" → [SELECT] →
 Go to step 4.
 - 3 [CALL BLOCK]
 - 4 (♣): "Yes" → [SELECT]
 - **5** Edit the phone number if necessary (24 digits max.).
 - 6 [SAVE] → [OFF]

Base unit

- 1 [CID]
- 2 [\$]: Select the entry to be blocked.
 - To edit the number: Press [EDIT] repeatedly until the phone number is shown in the 10-digit format.
- 3 [SAVE]
- 4 [♣]: "Call block" → [SELECT]
- **5** [♠]: "Yes" → [SELECT]
- 6 Edit the phone number if necessary (24 digits max.).
- 7 $[SAVE] \rightarrow [EXIT]$

Adding call blocked numbers manually

Handset

- 1 [CALL BLOCK]
- 2 [♠]: "Block a single number" →
 [SELECT]
- 3 [MENU] \rightarrow [\$]: "Add" \rightarrow [SELECT]
- 4 Enter the phone number (24 digits max.).
- 5 [SAVE] → [OFF]

Base unit

- 1 (MENU)#217
- $\left(\begin{bmatrix} \\ \\ \\ \end{bmatrix} \right)$: "Block a single #" \rightarrow [SELECT] \rightarrow [ADD]
- 3 Enter the phone number (24 digits max.).
- 4 [SAVE] → [EXIT]

Storing a range of number

Handset

- 1 [CALL BLOCK]
- 2 [♣]: "Block range of numbers" →
 [SELECT]
- 3 [MENU] \rightarrow [\$]: "Add" \rightarrow [SELECT]
- 4 Enter the desired number (2-8 digits).
- 5 $[SAVE] \rightarrow [OFF]$

Base unit

- 1 (MENU)#217
- 2 [♣]: "Block range of #" →
 [SELECT]
- 3 [ADD]
- 4 Enter the desired number (2-8 digits).
- 5 [SAVE] \rightarrow [EXIT]

Blocking incoming calls that have no phone number

You can block calls when no phone number is provided, such as private callers or out of area calls.

Handset

- 1 [CALL BLOCK]
- 2 [♣]: "Block unknown CID" →
 [SELECT]
- 3 [♠]: Select the desired setting. → [SAVE] → [OFF]

Base unit

1 (MENU) #240

2 [♣]: Select the desired setting. → [SAVE] → [EXIT]

Setting not to ring once for blocked call

If you do not want the unit to sound one ring for calls from phone numbers stored in the call block list, select "No". The default setting is "Yes".

Handset

- 1 [CALL BLOCK]
- 2 [♣]:"One ring for blocked call"
 → [SELECT]
- 3 [♣]: Select the desired setting. → [SAVE] → [OFF]

Base unit

- 1 [MENU]#173
- 2 (♣): Select the desired setting. → (SAVE) → (EXIT)

Viewing/editing/erasing call block numbers

Handset

- 1 [CALL BLOCK]
- 2 [♠]: "Block a single number" OF
 "Block range of numbers" →
 [SELECT]
- **3** (\$): Select the desired entry.
 - After viewing, press (OFF) to exit.
- 4 To edit a number:

 [EDIT] → Edit the number. → [SAVE]

 → [OFF]

To erase a number: [ERASE] \rightarrow [\diamondsuit]: "Yes" \rightarrow [SELECT] \rightarrow [OFF]

Base unit

- 1 (MENU)#217
- 2 (♣): "Block a single #" Or "Block range of #" → [SELECT]

- 3 (*): Select the desired entry.
 - After viewing, press [EXIT] to exit.
 - To edit a number:

[EDIT] → Edit the number. → [SAVE] \rightarrow [EXIT]

To erase a number:

 $\begin{array}{l} \texttt{[ERASE]} \rightarrow \texttt{[\updownarrow]} \texttt{: "Yes"} \rightarrow \texttt{[SELECT]} \\ \rightarrow \texttt{[EXIT]} \end{array}$

Note:

 When editing, press the desired dial key to add digits and press [CLEAR] to erase digits.

Erasing all call block numbers

Handset

- 1 [CALL BLOCK]
- 2 [♠]: "Block a single number" OF
 "Block range of numbers" →
 [SELECT]
- 3 [MENU] → [♣]: "Erase all" → [SELECT]
- 4 (♣): "Yes" → [SELECT]
- 5 [♣]: "Yes" → [SELECT] → [OFF]

Base unit

- 1 (MENU)#217
- 2 [♣]: "Block a single #" Of "Block range of #" → [SELECT]
- 3 [ERASE]
- 4 (♣): "Yes" → [SELECT]
- 5 ($\$): "Yes" \rightarrow [SELECT] \rightarrow [EXIT]

Phonebook

Phonebook

You can add 3,000 names (16 characters max.) and phone numbers (24 digits max.) to the phonebook, and assign each phonebook entry to the desired group (page 35). The following groups are available:

- Group 1: "Home"*1 (default)
- Group 2: "Cell 1"*1
- Group 3: "Cell 2"*1
- Group 4-9: You can change the group name for each group.
- *1 For groups 1-3, the group names cannot be changed.

Important:

- All entries can be shared by the base unit and any registered handset.
- You can copy phonebook entries from a Bluetooth cellular phone to the unit's phonebook (page 57).

Adding phonebook entries

Handset

- $[\blacktriangleleft] \square \rightarrow [MENU]$
- [♣]: "Add new entry" → [SELECT]
- 3 Enter the party's name. \rightarrow [OK]
- 4 Enter the party's phone number. → [OK]
- [♠]: Select the desired group. → [SELECT] 2 times → [OFF]

Character table for entering names

While entering characters, you can switch between uppercase and lowercase by pressing \times (A \rightarrow a).

Key	Character						
1	&	,	()	*	,	
	_		1	1			
2	Α	В	С	2			
	а	b	С	2			
3	D	Е	F	3			
	d	е	f	3			

Key	Character					
4	G	Н	I	4		
	g	h	i	4		
5	J	K	L	5		
	j	k	ı	5		
6	М	Ν	0	6		
	m	n	0	6		
7	Р	Q	R	S	7	
	р	q	r	s	7	
8	Т	U	V	8		
	t	u	٧	8		
9	W	Χ	Υ	Z	9	
	w	Х	у	z	9	
0	u	0				
#	#					

- To enter another character that is located on the same dial key, first press [►] to move the cursor to the next space.
- If you do not press any dial key within 2 seconds after entering a character, the character is fixed and the cursor moves to the next space.
- _ in the above table represents a single space.

Erasing the character or number

Press $[\blacktriangleleft]$ or $[\blacktriangleright]$. \rightarrow [CLEAR]

 Press and hold [CLEAR] to erase all characters or numbers.

Storing a redial list number to the phonebook

Phone numbers of up to 24 digits can be stored in the phonebook.

Handset

- When a cellular phone is paired:
 - 【►】REDIAL
 - []: Select the desired phone number. → [MENU]
 - $\{ \}$: "Save" $\rightarrow \{ \}$

- **4** To store the name, continue from step 3, "Editing entries", page 36.
- When a cellular phone is not paired:
 - 1 (►) REDIAL
 - 2 [♣]: Select the desired phone number.
 → [SAVE]
 - **3** To store the name, continue from step 3. "Editing entries", page 36.

Base unit

- 1 [REDIAL]
- (♣): Select the desired phone number.
 → [SAVE] → [EXIT]

Note for base unit:

- If you stored redial list number to the phonebook using the base unit, the entry is automatically assigned to "Home".
- If you want to edit the caller name or the group, you can do so using the handset (page 36).

Storing caller information to the phonebook

Handset

- When a cellular phone is paired:
 - 1 [v] CID
 - 2 [♣]: Select the desired entry. → [SELECT]
 - 3 [SAVE]
 - 4 (♣): "Phonebook" → [SELECT]
 - **5** Continue from step 3, "Editing entries", page 36.
- When a cellular phone is not paired:
 - 1 [▼] CID
 - 2 [♣]: Select the desired entry. → [MENU]
 - To edit the number:
 - [♣]: "Edit" → [SELECT]
 Press [EDIT] repeatedly until the phone number is shown in the

desired format. And then, press [SAVE]. Go to step 4.

- [♣]: "Save caller ID" → [SELECT]
- 4 [♣]: "Phonebook" → [SELECT]
- **5** Continue from step 3, "Editing entries", page 36.

Base unit

- 1 [CID]
- 2 (*): Select the desired entry.
 - To edit the number, press [EDIT] repeatedly until the phone number is shown in the desired format.
- 3 [SAVE]
- 4 [♣]: "Phonebook" → [SELECT]
- 5 [EXIT]

Note for base unit:

- If you stored caller information to the phonebook using the base unit, the entry is automatically assigned to "Home".
- If you want to edit the caller name or the group, you can do so using the handset (page 36).

Groups

Groups can help you find entries in the phonebook quickly and easily. You can change the group name for groups 4-9 ("Friends", "Family", etc.). By assigning different ringer tones for different groups of callers, you can identify who is calling (ringer ID), if you have subscribed to Call Display service.

Changing group names/setting ringer ID

Handset

- 1 (◄) □ → [MENU]
- 2 [♣]: "Group" → [SELECT]
- 3 [♣]: Select the desired group. → [SELECT]
 - If you selected "Home", "Cell 1", or "Cell 2", go to step 5.

Phonebook

- To change group names
 - $[\ \ \]$: "Group name" \rightarrow [SELECT] \rightarrow Edit the name (10 characters max.). \rightarrow [SAVE]
- 5 To set group ringer tone
 - (\$): Select the current setting of the group ringer tone. \rightarrow [SELECT] \rightarrow [\updownarrow]: Select the desired ringer tone. → [SAVE]
- 6 [OFF]

Finding and calling from a phonebook entry

Once you have found the desired entry using one of the following 4 methods, make a call with your unit.

■ Using a cellular line:

Handset

- [CELL]
 - The unit starts dialing when:
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).
- $[\begin{tabular}{l} \begin{tabular}{l} \begin{tab$

Base unit

Press (CELL 1) or (CELL 2).

■ Using a landline:

Handset



Base unit

[⊕]

Scrolling through all entries

Handset / Base unit

- Proceed with the operation for your unit. Handset: [◄] [Base unit: (D)
- 2 [\$]: Select the desired entry.

Searching by first character

Handset / Base unit

- Proceed with the operation for your unit. Handset: [◄] □ Base unit: (1111)
- Press the dial key (0 9 or #) which contains the character you are searching for (page 34).
- [\$]: Scroll through the phonebook if necessary.

Searching by guery

You can parrow down the search to enter the first characters of a name.

Handset / Base unit

- Proceed with the operation for your unit. Handset: $(\blacktriangleleft) \square \rightarrow \mathbb{R}$
 - Base unit: $(\square) \rightarrow \mathbb{R}$
- To search for the name, enter the first characters (up to 4) in uppercase (page 34).
- [OK]
- (\$): Scroll through the phonebook if necessary.

Searching by group

Handset / Base unit

- 1 Proceed with the operation for your unit. Handset: (◄) □ Base unit: []
- 2 [GROUP]
- [\$]: Select the group you want to search.
 - → [SELECT] • If you select "All groups", the unit
- ends the group search. [\$]: Select the desired entry.

Editing entries

Handset

Find the desired entry (page 36).

- 2 [MENU] \rightarrow [\diamondsuit]: "Edit" \rightarrow [SELECT]
- 3 Edit the name if necessary. → [OK]
- 4 Edit the phone number if necessary. → [OK]
- 5 [♣]: Select the desired group (page 35).
 → [SELECT] 2 times → [OFF]

Erasing entries

Erasing an entry

Handset

- 1 Find the desired entry (page 36).
- 2 [MENU] \rightarrow [$^{\blacktriangle}$]: "Erase" \rightarrow [SELECT]
- 3 (♣): "Yes" → [SELECT] → [OFF]

Base unit

- 1 Find the desired entry (page 36).
- 2 [ERASE] → [\$]: "Yes" → [SELECT]
 → [EXIT]

Erasing all entries

Handset

- 1 [◄] m → [MENU]
- 2 (♣): "Erase all" → [SELECT]
- 3 [♠]: Select the desired group. → [SELECT]
- 4 [♠]: "Yes" → [SELECT]
- 5 ($\ \$): "Yes" \rightarrow [SELECT] \rightarrow [OFF]

Base unit

- 2 [♣]: Select the desired group. → [SELECT]
- 3 (♣): "Yes" → [SELECT]
- **4** (♠): "Yes" → [SELECT]

Chain dial

This feature allows you to dial phone numbers in the phonebook while you are on a call. This feature can be used, for example, to dial a

calling card access number or bank account PIN that you have stored in the phonebook, without having to dial manually.

Handset / Base unit

- 1 Proceed with the operation for your unit. Handset: During an outside call, press [◄] □□.

 Base unit: During an outside call, press [□□].
- 2 (\$): Select the desired entry.
- 3 Press [CALL] to dial the number.

Note:

- When storing a calling card access number and your PIN in the phonebook as one phonebook entry, press [A] (Pause) to add pauses after the number and PIN as necessary (page 21).
- If you have rotary/pulse service, you need to press ※ (TONE) before pressing 【◄】 ☐ on the handset or 【□□】 on the base unit in step 1 to change the dialing mode temporarily to tone. When adding entries to the phonebook, we recommend adding ※ (TONE) to the beginning of phone numbers you wish to chain dial (page 34).

Speed dial

You can assign 1 phone number to each of the dial keys (1 to 9) on the handset.

Adding phone numbers to speed dial keys

Handset

- By entering phone numbers:
 - 1 Press and hold the desired speed dial key (1 to 9). → [ADD]
 - **2** [♠]: "Manual" → [SELECT]
 - 3 Enter the party's name (16 characters max.). → [OK]
 - Enter the party's phone number (24 digits max.). → [OK]
 - 5 (SELECT) \rightarrow [OFF]

Phonebook

■ From the phonebook:

- Press and hold the desired speed dial key ($\boxed{1}$ to $\boxed{9}$). \rightarrow [ADD]
- [♣]: "Phonebook" → [SELECT]
- **3** [♠]: Select the desired entry.
- 4 $[SAVE] \rightarrow [OFF]$

Note:

 If you edit a phonebook entry which is assigned to a speed dial key, the edited entry does not transfer to the speed dial key.

Editing an entry

Handset

- Press and hold the desired speed dial key $(1 to 9). \rightarrow [MENU]$
- [♠]: "Edit" → [SELECT]
- 3 Edit the name if necessary. → [OK]
- Edit the phone number if necessary. → [OK]
- $[SELECT] \rightarrow [OFF]$

Erasing an entry

Handset

- Press and hold the desired speed dial key $(1 to 9). \rightarrow [MENU]$
- [♠]: "Erase" → [SELECT]
- $[\ \ \]$: "Yes" \rightarrow [SELECT] \rightarrow [OFF]

Viewing an entry/Making a call

Handset

■ Using a cellular line:

- Press and hold the desired speed dial key (1 to 9).
- [CELL]
 - The unit starts dialing when:
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).

[\$]: Select the desired cellular phone. → [SELECT]

Using a landline:

- Press and hold the desired speed dial key (1 to 9).
- To make a call, press [].

For assistance, visit www.panasonic.ca/english/support

TG175CSK (en) _0324_ver011. pdf

38

Menu list

To access the features, there are 2 methods.

Handset / Base unit

- Scrolling through the display menus
 - [MENU]
 - 2 Press [▼] or [▲] to select the desired main menu. → [SELECT]
 - 3 Press (▼) or (▲) to select the desired item from the next sub-menus. → [SELECT]
 - 4 Press (▼) or (▲) to select the desired setting. → (SAVE)
- Using the direct command code
 - **[MENU]** → Enter the desired code.

Example: Press [MENU]#101.

For available code:

- Handset: see page 39.
- Base unit: see page 46.
- 2 Select the desired setting. → [SAVE]

- To exit the operation, press [OFF] on the handset or [EXIT] on the base unit.
- In the following table, < > indicates the default settings.
- In the following table, figure indicates the reference page number.
- Display menu order and sub-menu may vary depending on your model.

Display menu tree and direct command code table

■ Handset

Main menu: "Phonebook"

Operation	Code	
Viewing the phonebook entry.	#280	36

Main menu: → "Caller list"

Operation	Code	Ġ
Viewing the caller list.	#213	55

Main menu: @ "Answering device"

Sub-menu 1	Sub-menu 2	Settings	Code	G
Play new message	_	_	#323	64
Play all message	_	_	#324	64
Erase all message*1	-	_	#325	64

Sub-menu 1	Sub-menu 2	Settings	Code	G
Greeting	Record greeting*1	_	#302	62
	Check greeting	-	#303	63
	Pre-recorded*1 (Reset to pre-recorded greeting)	_	#304	63
New message alert*1	Outgoing call - On/Off	On <off></off>	#338	65
	Outgoing call - Notification to	-		
	Outgoing call - Remote code	Activate <inactivate></inactivate>		
	Base unit beep	On <off></off>	#339	65
Settings	Ring count*1	2-7 rings <4 rings> Toll saver	#211	67
	Recording time*1	1 min <3 min> Greeting only*2	#305	68
	Remote code*1	<111>	#306	66
	Screen call	<on> Off</on>	#310	67
Answer on*1	_	_	#327	62
Answer off*1	-	_	#328	62

Main menu: ☑️ "Voicemail access"*3

Operation	Code	G
Listening to voicemail messages.	#330	70

Main menu: (·) "Intercom"

Operation	Code	G
Paging the desired unit.	#274	30

Main menu: (3) "Bluetooth"

Sub-menu 1	Sub-menu 2	Settings	Code	G
Link to cell	Connect*1/	_	#6251*5	18
- 1:Add new	Disconnect*1		#6252*6	
device*4 (for CELL 1)	Ringer volume	Off-6 <6>	#6281*5	21
- 2:Add new			#6282*6	
device*4	Ringer tone*7	<tone 2="">*5</tone>	#6291*5	-
(for CELL 2)		<tone 4="">*6</tone>	#6292*6	
	Select unit to	Handset 1-6	#6271*5	17
	ring*1	<a11></a11>	# 6272 *6	
	Ring as cell (limited)*1	<on (with<br="">Talking CID)></on>	#6141*5	17
		On (without Talking CID) Off	#6142 *6	
	Alert settings*1	<0n>	#6101*5	59
	- Alert On/Off	Off	#6102*6	
	Alert settings*1	<0n>	#6031*5	59
	- Voice alert	Off #6032*6	#6032*6	
	Alert settings*1,*8	<tone 1="">*5</tone>	#6041*5	60
	- Alert tone	<tone 2="">*6</tone>	# 6042 *6	
	Pair	_	#6241*5	16
			#6242 *6	
	Unpair	_	#6111*5	16
			#6112*6	
Phonebook transfer	-	_	#618	57
Headset	Add new device*4	_	#621	60
	Connect*1/ Disconnect*1	_	#622	60
	Pair	-	#621	60
	Unpair	_	#612	61

Sub-menu 1	Sub-menu 2	Settings	Code	G
Settings	Auto connect*1	<pre><1 min> 3 min 5 min 10 min Off</pre>	#632	18
	Cell area code*1	_	#633	19
	Cell line only mode*1	On <off></off>	#157	18
	Cell line select - Handset	Cellphone 1*4 Cellphone 2*4 <manual></manual>	#634	19
	Cell line select - Base unit*1	<cellphone 1="">*4 Cellphone 2*4</cellphone>	# * 634	
	Set PIN*1	<0000>	#619	19
	International code*1	_	#117	57
	Country code*1	_	#118	
	Trunk prefix*1	_	#119	

Main menu: ⊕ "Set date & time"

Sub-menu 1	Sub-menu 2	Settings	Code	G
Date and time*1	_	_	#101	15
Memo alarm	Alarm1-3	Once Daily Weekly <off></off>	#720	48
Time adjustment*1,*9	_	<caller auto="" id=""> Manual</caller>	#226	-

Main menu: ■□ "Speed dial"

Operation	Code	Ġ
Viewing the speed dial entry.	#261	37

Main menu: **▶** "Settings"

Sub-menu 1	Sub-menu 2	Settings	Code	G
Ring adjustments	Ringer volume*3	Off-6 <6>	#160	-
	Ringer tone*3, *7, *10 (Handset)	<tone 1=""></tone>	#161	-
	Interrupt tone*11	<on> Off</on>	#201	24
	Night mode - On/Off	On <off></off>	#238	49
	Night mode - Start/End	<11:00 PM/06:00 AM>	#237	49
	Night mode - Select group	Home Cell 1 Cell 2 Group 4-9	#241	49
Set date & time	Date and time*1	_	#101	15
	Memo alarm - Alarm1-3	Once Daily Weekly <off></off>	#720	48
	Time adjustment*1,*9	<caller auto="" id=""></caller>	#226	-
Talking caller ID (Talking Call Display)	_	<on> Off</on>	#162	53
Key detector	Change name*1	Detector1	#6561	_
setting*12 - 1:Add new device		Detector2*14	#6562*14	
(for Detector1)*13		Detector3*14	#6563*14	
- 2:Add new device		Detector4*14	#6564*14	
(for Detector2) - 3:Add new device	Registration		#6571	-
(for Detector3) - 4:Add new device (for Detector4)			#6572*14	
			#6573*14	
			#6574*14	
	Deregistration	-	#6581	-
			#6582*14	
			#6583*14	
			#6584*14	

Sub-menu 1	Sub-menu 2	Settings	Code	G
Call block*1	Block a single number	-	#217	31
	Block range of numbers	_		32
	Block unknown CID (CID: Call Display)	Block <unblock></unblock>	#240	32
	One ring for blocked call	<yes></yes>	#173	33
Speed dial	_	_	#261	37
Record greeting*1	_	_	#302	62
Voicemail*3	Save VM access#*1 (VM: Voicemail)	-	#331	69
	VM tone detect*1	<on> Off</on>	#332	69
LCD contrast (Display contrast)	_	Level 1-4 <2>	#145	-
Handset name	_	-	#104	51
Display name	_	On <off></off>	#105	52
Auto intercom	_	On <off></off>	#273	30
Key tone	_	<on> Off</on>	#165	_
Auto talk*15	_	On <off></off>	#200	21

Sub-menu 1	Sub-menu 2	Settings	Code	G
Set tel line*3 Set dial mode*1		Pulse <tone></tone>	#120	15
	Set flash time*1,*16	900 ms <700 ms> 600 ms 400 ms 300 ms 250 ms 200 ms 160 ms 110 ms 100 ms 90 ms 80 ms	#121	21
	Set line mode*1,*17	A 	#122	-
	C. WTG options*1 (Call Waiting Deluxe options)	On <off></off>	#215	54
Privacy mode ^{*1} -		On <off></off>	#194	23, 28
Registration	Register handset	-	#130	52
	Deregistration*2	_	#131	52
Power failure -		<auto></auto>	#152	24
Change language	Display	<english> Français</english>	#110	15
	Voice prompt*1	<english> Français</english>	#112	15

Main menu: ? "Customer support"

Operation	Code	G
Displaying customer support Web address.	#680	_

Main menu: 😂 "Baby monitor"

Sub-menu 1	Sub-menu 2	Settings	Code	G
On/Off	_	On <off></off>	#268	50
Sensitivity level	_	Low <middle> High</middle>	#269	51

Main menu: (2) "Key detector"*12

Sub-menu 1	Sub-menu 2	Settings	Code	G
Search	_	-	#655	-
Battery check	_	-		

■ Base unit

Main menu: III "Phonebook"

Operation	Code	G
Viewing the phonebook entry.	#280	36

Main menu: → "Caller list"

Operation	Code	G
Viewing the caller list.	#213	55

Main menu: ☑ ✗ "Answer device"

Sub-menu 1	Sub-menu 2	Settings	Code	G
Screen call	_	<0n>	#310	67
		Off		

Main menu: (3) "Bluetooth"

Sub-menu 1	Sub-menu 2	Settings	Code	G
Link to cell*18	Ringer volume	off-6 <1>	#6281*5	27
- Cellular phone 1*4			#6282 *6	
Cellular phone 2*4	Alert settings*1	<0n>	#6101*5	59
	- Alert On/Off	Off	#6102*6	
	Alert settings*1	<0n>	#6031*5	59
	- Voice alert	Off	#6032*6	
Cell line	<cellphone 1="">*4 Cellphone 2*4</cellphone>	-	#634	19

Main menu: F "Settings"

Sub-menu 1	Sub-menu 2	Settings	Code	
Ring adjustment	Ringer volume*3	Off-6 <1>	#160	_
	Interrupt tone*11	<on> Off</on>	#201	28
	Night mode - On/Off	On <off></off>	#238	49
	Night mode - Start/End	<11:00 PM/ 06:00 AM>	#237	49
	Night mode - Select group	Home Cell 1 Cell 2 Group 4-9	#241	49
Talking CID (Talking Call Display)	_	On <off></off>	#162	53
Call block*1 Block a single #		_	#217	31
	Block range of #	_		32
	Block unknown	Block <unblock></unblock>	#240	32
Ring once		<yes></yes>	#173	33
LCD contrast (Display contrast)	_	Level 1–6 <3>	#145	1
Auto intercom	-	On <off></off>	#273	30
Change language (Display)	_	<english> Français</english>	#110	15

Main menu: ? "Cust. Support"

Operation		Ġ
Displaying customer support Web address.	#680	_

- *1 If you program these settings using one of the units, you do not need to program the same item using another unit.
- *2 This menu is not displayed when scrolling through the display menus. It is only available in direct command code.
- *3 When the cellular line only mode is turned on, these menus are not displayed (page 18).
- *4 After the Bluetooth device is paired, the device name is displayed.
- *5 For CELL 1
- *6 For CELL 2
- *7 The preset melodies in this product ("Tone 3" "Melody 10") are used with permission of © 2009 Copyrights Vision Inc.
- *8 The preset melodies in this product ("Tone 1" and "Tone 2") are used with permission of © 2013 Copyrights Vision Inc.

For assistance, visit www.panasonic.ca/english/support

47

- This feature allows the unit to automatically adjust the date and time each time caller information including date and time is received.
 - To turn this feature on, select "Caller ID auto". To turn this feature off, select "Manual". (Call Display subscribers only)
- *10 If you subscribe to a distinctive ring service, select a tone (tone 1 or 2). If you select a melody, you cannot distinguish lines by their ringers.
- *11 This tone lets you know when you receive an outside call while you are on another line or an intercom call. If you select "on", the tone sounds 2 times.
- *12 This setting is available when you have the key detector (KX-TGA20). Read the installation manual for more information on the key detector.
- *13 For models with supplied key detectors, the display shows "1: Detector1".
- *14 If you register 2 or more key detectors.
- *15 If you subscribe to a Call Display service and want to view the caller's information after lifting up the handset to answer a call, turn off this feature.
- *16 The flash time depends on your telephone exchange or host PBX. Contact your PBX supplier if necessary.
- *17 Generally, the line mode setting should not be changed. This setting automatically maintains receiver volume at the proper level depending on the current telephone line condition. Set the line mode to "A" if telephone line condition is not good.
- *18 This setting is available when a cellular phone is paired.

Alarm

An alarm sounds at the set time for 1 minute and is repeated 5 times at 5 minute intervals (snooze function). A text memo can also be displayed for the alarm. A total of 3 separate alarm times can be programmed for each handset. You can set one of 3 different alarm options (once, daily, or weekly) for each alarm time.

Important:

· Make sure the unit's date and time setting is correct (page 15).

Handset

- (MENU)#720
- 2 [♠]: Select the desired alarm. → (SELECT)
- [♠]: Select the desired alarm option. → (SELECT)

"Off" Turns alarm off. Go to step 10. An alarm sounds once at the set time.

"Daily"

An alarm sounds daily at the set time. Go to step 5.

"Weekly"

Alarm sounds weekly at the set time(s).

- Proceed with the operation according to your selection in step 3.
 - Once:

Enter the desired month and date. → [OK]

- Weekly:
 - (\$): Select the desired day of the week and press [SELECT]. \rightarrow [OK]
- Set the desired time.
- \mathbb{R} : Select "AM" or "PM". \rightarrow [OK]
- Enter a text memo (10 characters max.). \rightarrow [OK]
- $[\ \]$: Select the desired alarm tone. \rightarrow (SELECT)
 - We recommend selecting a different ringer tone from the one used for outside calls.
- []: Select the desired snooze setting. → [SAVE]

10 [SELECT] \rightarrow [OFF]

Note:

- Press [STOP] to stop the alarm completely.
- When the handset is in use, the alarm will not sound until the handset is in standby mode.
- Press any dial key or [SNOOZE] to stop the sound but keep the snooze function activated
- If you want to make an outside call when the snooze function is activated, please stop the snooze function before making the call

Night mode

Night mode allows you to select a period of time during which the handset and/or base unit will not ring for outside calls. This feature is useful for time periods when you do not want to be disturbed, for example, while sleeping. Night mode can be set for each unit. Using the phonebook's group feature (page 35), you can also select groups of callers whose calls override night mode and ring the unit (Call Display subscribers only).

Important:

- Make sure the unit's date and time setting is correct (page 15).
- If you have set the alarm, the alarm sounds even if the night mode is turned on.

Turning night mode on/off

Handset

- 1 (MENU)#238
- 2 [♣]: Select the desired setting. → [SAVE]
 - If you select "off", press [OFF] to
- 3 Enter the desired hour and minute you wish to start this feature.
- 4 \mathbb{R} : Select "AM" or "PM". \rightarrow [OK]
- 5 Enter the desired hour and minute you wish to end this feature.
- 6 ★: Select "AM" or "PM".

7 $[SAVE] \rightarrow [OFF]$

Base unit

- 1 [MENU]#[2]3[8]
- 2 (♣): Select the desired setting. → (SAVE)
 - If you select "off", press [EXIT] to
- 3 Enter the desired hour and minute you wish to start this feature.
- **4 [AM/PM]**: Select "**AM**" or "**PM**". → **[OK]**
- Enter the desired hour and minute you wish to end this feature.
- 6 [AM/PM]: Select "AM" or "PM".
- 7 [SAVE] → [EXIT]

Changing the start and end time

Handset / Base unit

- 1 (MENU)#237
- 2 Continue from step 3, "Turning night mode on/off", page 49.

Selecting groups to bypass night mode

Handset / Base unit

- 1 [MENU]#241
- 2 [♣]: Select the desired group. → [SELECT]
 - "

 " is displayed next to the selected group numbers.
 - To cancel the selected group:
 - [♣]: Select the group. → Press
 [SELECT] again. "✓" disappears.
 - [SAVE]

3

4 Proceed with the operation for your unit. Handset: [OFF] Base unit: [EXIT]

Baby monitor

This feature allows you to listen in on a room where another handset is located, allowing

you to easily monitor from different areas of the house or place. The monitored handset (placed in a baby's room, for example) will automatically call the monitoring handset. base unit, or the phone number stored when it detects sound.

Important:

- You should perform a test run of the baby monitor procedure to ensure that the baby monitor feature is set correctly. For example, test its sensitivity. Check the connection if you are diverting the baby monitor to an outside line.
- This feature should not be used as a substitute for a medical or caregiver's supervision. It is the caregiver's responsibility to stay close enough to handle any eventuality.

Note:

- If the unit is connected to a PBX system. you cannot set the baby monitor.
- During the monitoring mode, battery consumption is faster than usual. We recommend leaving the monitored handset on the base unit or charger.
- The monitored handset never rings while it is being monitored. If the base unit is placed near the monitored handset, we recommend turning off the base unit ringer volume (page 46, 47).

Setting the baby monitor

Perform the setting operation with the handset to be monitored (for example, the handset placed in a baby's room).

To monitor with a unit

The internal baby monitor feature is available:

- between handsets
- between a handset and the base unit

Handset

- (MENU)#268
- $\{ \$]: "On" $\rightarrow \{ \}$
- [\$]: Select the desired unit's number to monitor with. \rightarrow [SAVE]
 - "Baby monitor" will be displayed.

 The registered unit's name/number is displayed.

Note:

When this feature is on, another handset or the base unit can hear the monitored handset by making an intercom call.

To monitor from an outside line

If you enable this feature, the unit will call a pre-programmed phone number when the handset detects sound. After you answer the call, you can listen in on the room where the handset is located.

This feature is only available for landline.

Handset

- From the phonebook:
 - [MENU]#268
 - $[\]$: "On" \rightarrow [SELECT]
 - [\$]: Select "Outgoing call" to monitor from an outside line. \rightarrow $[EDIT] \rightarrow [ADD]$
 - [♠]: "Phonebook" → [SELECT]
 - (♠): Select the phonebook entry. → [SAVE]
 - "Baby monitor" will be displayed.

Note:

- If you edit a phonebook entry which is assigned for monitoring, the edited entry does not transfer to the monitor.
- By entering phone numbers:
 - (MENU)#268
 - $\{ \} : "on" \rightarrow \{ SELECT \}$
 - [\$]: Select "Outgoing call" to monitor from an outside line. \rightarrow $[EDIT] \rightarrow [ADD]$
 - [♠]: "Manual" → [SELECT]
 - Enter the desired name. \rightarrow [OK]
 - Enter the desired number. \rightarrow [OK] \rightarrow [SELECT]
 - "Baby monitor" will be displayed.

Note:

The registered name/number is displayed.

Turning off the baby monitor

The monitored handset cannot be used while baby monitor is set to "on".

Handset

- Press [MENU] on the handset being monitored.
- 2 [♣]: "On/Off" → [SELECT]
- 3 ($\$): "off" \rightarrow [SELECT] \rightarrow [OFF]

Editing an outside monitoring number

Handset

- Press [MENU] on the handset being monitored.
- 2 [♣]: "On/Off" → [SELECT]
- 3 [♠]: "on" → [SELECT]
- **4** (♣): Select the outside line. → **[EDIT]**
- 5 [MENU] \rightarrow [\updownarrow]: "Edit" \rightarrow [SELECT]
- **6** Edit the name if necessary. \rightarrow **[OK]**
- 7 Edit the phone number if necessary. → [OK] → [SELECT]

Erasing an outside monitoring number

Handset

- Press [MENU] on the handset being monitored.
- 2 [♣]: "On/Off" → [SELECT]
- 3 (♣): "on" → [SELECT]
- 4 (♣): Select the outside line. → (EDIT)
- 5 [MENU] \rightarrow [\updownarrow]: "Erase" \rightarrow [SELECT]
- $\{ \ \ \ \ \}$: "Yes" \rightarrow [SELECT] \rightarrow [OFF]

Baby monitor sensitivity

You can adjust the sensitivity of the baby monitor. Increase or decrease the sensitivity to adjust the sound level needed to trigger the baby monitor feature.

 This feature cannot be set during a monitoring call.

Handset

- Press [MENU] on the handset being monitored.
- 3 [♠]: Select the desired setting. → [SAVE] → [OFF]

Answering the baby monitor

- When monitoring with a unit:
 Handset: Press [] to answer a call.
 Base unit: Press [] to answer a call.
 If you want to respond from the monitoring unit, press [MUTE].
 - The monitoring unit will answer calls automatically when the auto intercom feature is set to "on" (page 30).

Note:

- If you receive an outside call when communicating with the monitored handset, the interrupt tone sounds.
 - To answer the call with the handset, press [OFF], then press [].
 - To answer the call with the base unit, press [♣] 3 times.*1
- *1 If [MUTE] is pressed, press [♣] 2 times.
- When monitoring from an outside line: Answer the call.

If you want to respond from your monitoring phone, press #1 using tone dialing.
You can turn off the baby monitor feature by pressing #0.

Note:

 The unit disconnects the call automatically after 2 minutes.

Other programming

Changing the handset name

The default handset name is "Handset 1" to "Handset 6". You can customize the name of each handset ("Bob", "Kitchen", etc.). This is

useful when you make intercom calls between handsets. To display the handset name in standby mode, turn on the handset name display feature (page 52).

Handset

- 1 (MENU)#104
- 2 Enter the desired name (10 characters max.).
- 3 $[SAVE] \rightarrow [OFF]$

Displaying the handset name

You can select whether or not the handset name is displayed in standby mode. The default setting is "off".

Handset

- 1 (MENU)#105
- 2 [♣]: Select the desired setting. → [SAVE] → [OFF]

Registering a unit

Operating additional units

Additional handsets

Up to 6 handsets can be registered to the base unit.

Important:

 See page 4 for information on the available model.

Registering a handset to the base unit

The supplied handset and base unit are pre-registered. If for some reason the handset is not registered to the base unit, re-register the handset.

1 Handset: (MENU)#11310

52

2 Base unit: Press and hold [LOCATOR] for about 5 seconds.

- If all registered handsets start ringing, press [LOCATOR] again to stop, then repeat this step.
- 3 Handset:

Press **[OK]**, then wait until a long beep sounds.

Deregistering a handset

A handset can cancel its own registration to the base unit, or other handsets registered to the same base unit. This allows the handset to end its wireless connection with the system.

Handset

- 1 (MENU)#131
 - All handsets registered to the base unit are displayed.
- 2 [♣]: Select the handset you want to cancel. → [SELECT]
- 3 (\diamondsuit): "Yes" \rightarrow [SELECT] \rightarrow [OFF]

Using Call Display service

Important:

 This unit is Call Display compatible. To use Call Display features, you must subscribe to a Call Display service. Contact your phone service provider for details.

Call Display features

Handset / Base unit

When an outside call is being received, the caller information is displayed.

Caller information for the last 50 callers is logged in the caller list from the most recent call to the oldest.

- If the unit cannot receive caller information, the following is displayed:
 - "Unavailable"*1/"Unavailable Name & No."*2: The caller dials from an area which does not provide a Call Display service.
 - "Private caller"*1/"Private"*2 The caller requests not to send caller information
 - "Long distance"*1/"Long dist."*2: The caller makes a long distance call.
- If the unit is connected to a PBX system, caller information may not be properly received. Contact your PBX supplier.
- Handset
- Base unit

Missed calls

Handset / Base unit

If a call is not answered, the unit treats it as a missed call. The display shows "Missed call".

Note:

- Even when there are unviewed missed calls, "Missed call" disappears from the standby display if the following operation is performed by one of the units:
 - A handset is replaced on the base unit or charger.
 - Pressing (OFF) on a handset.
 - Pressing (EXIT) on the base unit.

Phonebook name display

When caller information is received and it matches a phone number stored in the phonebook, the stored name in the phonebook is displayed and logged in the caller list

Talking Call Display

Handset / Base unit

This feature lets you know who is calling without looking at the display.

To use this feature, you must:

- subscribe to a Call Display service of your phone service provider.
- turn this feature on (page 43, 47). When caller information is received, the handsets and/or base unit announce the caller's name or phone number received from your phone service provider following every
- Name pronunciation may vary. This feature may not pronounce all names correctly.
- Call Display service has a limit of how many characters can be displayed. If the caller's name is too long, the unit may not be able to display or announce the entire

Phonebook name announcement

When caller information is received and it matches a phone number stored in the phonebook, the stored name in the phonebook is announced

For Call Waiting Deluxe service users

To use Call Waiting Deluxe, you must subscribe to Call Waiting Deluxe from your phone service provider. This feature not only allows the unit currently in use to display the 2nd caller's information, but also offers you a variety of ways to deal with the 2nd call.

Important:

 Please contact your phone service provider for details and availability of this service in vour area.

Call Display Service

• This feature must be turned on before it can be used.

To turn Call Waiting Deluxe on/off

To use Call Waiting Deluxe, you must turn this feature on. The default setting is "off".

Handset

- [MENU]# 2 1 5
- [\$]: Select the desired setting.
- 3 [SAVE] \rightarrow [OFF]

Call Waiting Deluxe service options

When a 2nd call is received, you can choose how to handle the call by selecting an option shown on the unit display.

 Your phone service provider may not offer all of the options (page 54).

Displayed option	Function
Answer	Answers the waiting call, while keeping the 1st call on hold.
Hold	Holds the waiting call. The caller will hear the pre-recorded hold message played by your phone service provider.
Announce	The caller will hear the pre-recorded busy message played by your phone service provider (for example, "We are not available now.") and will then be disconnected.
Forward	Forwards the waiting call to the voicemail service provided by your phone service provider. You must subscribe to voicemail service to use this function.

Displayed option	Function
Drop	Disconnects (drops) the current call and answers the waiting call.
Conference	Answers the waiting call and combines it with the current call to make a conference call (3-party call).
Return	Returns to the waiting caller while keeping the current call on hold.
Drop caller1	Disconnects (drops) the 1st call during a conference call.
Drop caller2	Disconnects (drops) the 2nd call during a conference call.

To use Call Waiting Deluxe service

Handset / Base unit

- When you hear a Call Waiting tone during an outside call, press (FLASH).
 - The option menu is displayed.
- [♠]: Select the desired option. → [SELECT]
 - After selecting "Answer", "Hold", or "Conference", you can select another option. \rightarrow [FLASH] \rightarrow [\updownarrow]: Select the desired option. → [SELECT]

Note:

• To exit from the option menu, wait for 20 seconds

Caller list

Important:

 Make sure the unit's date and time setting is correct (page 15).

Viewing the caller list and calling back

■ Using a cellular line

Handset

- 1 [▼] CID
- 2 Press (▼) to search from the most recent call, or [A] to search from the oldest call.
- To call back, press [SELECT]. To exit, press [OFF].
- [CELL]
 - The unit starts dialing when:
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).
- 5 (♠): Select the desired cellular phone. → (SELECT)

Base unit

- 1 [CID]
- Press [▼] to search from the most recent call, or [A] to search from the oldest call.
- To call back, press [CELL 1] or [CELL To exit, press [EXIT].
- Using a landline

Handset / Base unit

- Proceed with the operation for your unit. Handset: [▼] CID Base unit: [CID]
- 2 Press (▼) to search from the most recent call, or [A] to search from the oldest call.
- Proceed with the operation for your unit. Handset:
 - To call back, press [].
 - To exit, press [OFF].

Base unit:

- To call back, press (♣).
- To exit, press (EXIT).

Note for handset and base unit:

- If the entry has already been viewed or answered, "√" is displayed.
- or 2 indicates the caller information was received from the cellular line.

Editing a caller's phone number

You can edit a phone number in the caller list by adding the long distance code "1" or removing its area code.

Handset

- When a cellular phone is paired:
 - 【▼】CID
 - [♠]: Select the desired entry. → [SELECT]
 - Press * (Edit) repeatedly until the phone number is shown in the desired format.
 - Using a cellular line:

To make a cellular call, continue from step 4, "Viewing the caller list and calling back", page 55. Using a landline:

- When a cellular phone is not paired:
 - 【▼】CID
 - [♠]: Select the desired entry. → (MENU)
 - [♠]: "Edit" → [SELECT]
 - Press [EDIT] repeatedly until the phone number is shown in the desired format.
 - 5 []

Base unit

- 1 [CID]
- 2 (\$): Select the desired entry.
- Press [EDIT] repeatedly until the phone number is shown in the desired format.
- Using a cellular line: Press [CELL 1] or [CELL 2]. Using a landline:

[♣]

• The number edited will not be saved in the caller list.

Call Display Service

Erasing selected caller information

Handset / Base unit

- Proceed with the operation for your unit. Handset: [▼] CID Base unit: [CID]
- 2 [\$]: Select the desired entry.
- 3 [ERASE] \rightarrow [$^{\vartriangle}$]: "Yes" \rightarrow [SELECT]
- 4 Proceed with the operation for your unit. Handset: [OFF] Base unit: [EXIT]

Erasing all caller information

Handset / Base unit

- Proceed with the operation for your unit. Handset: (▼) CID Base unit: [CID]
- [ERASE] \rightarrow [$^{♠}$]: "Yes" \rightarrow [SELECT]
- Handset: [OFF]

Copying phonebook from a cellular phone (phonebook transfer)

You can copy phonebook entries from the paired cellular phones or other cellular phones (not paired) to the unit's phonebook. A cellular phone must be compatible with Bluetooth wireless technology.

Important:

- Your cellular phone must support Phone Book Access Profile (PBAP) or Object Push Profile (OPP) specification.
- If a copied entry has 2 or more phone numbers, each phone number (6 max.) is stored as a separate entry with the same name
- If a phonebook entry includes additional data such as a picture, that entry may fail to copy to the base unit.
- If your cellular phone includes international call entries, set the conversion codes before copying (page 57).

1 Handset: (MENU)#618

2 Handset:

To copy from paired cellular phones:

- [♠]: Select the desired cellular phone. → [SELECT]
- Copied items are stored to the group ("Cell 1" or "Cell 2") which the cellular phone is paired to.

To copy from other cellular phones (not paired):

- $[^{\vartriangle}]$ "Other cell" \rightarrow [SELECT] \rightarrow
- $[\ \ \ \]$: Select the group you want to copy to. \rightarrow [SELECT]

Handset:

When "Use the cell to transfer phone book" is displayed: Go to step 4.

When "Select mode" menu is displayed:

[♠]: Select "Auto" or "Manual". →
[SELECT]

"Auto": Download all entries from the cellular phone automatically. Go to step 5.

"Manual": Copy entries you selected.

- "Select mode" menu is displayed only when the cellular phone supports PBAP (Phone Book Access Profile) for Bluetooth connection.
- Some cellular phones may require you to perform an operation on the cellular phone even if you select "Auto".

4 Cellular phone:

Follow the instructions of your cellular phone to copy phonebook entries.

- For other cellular phones (not paired), you need to search for and select the base unit. The Bluetooth PIN (default: "0000") may be required. If your cellular phone shows PassKey confirmation on its display, follow the directions to proceed.
- The entries being copied are displayed on the handset.

5 Handset:

Wait until "Completed" is displayed.

 You can continue copying other entries if necessary.

6 Handset: [OFF]

Note:

- Some copied entries may have characters which do not exist in the character table (page 34). These characters can be displayed but cannot be entered when editing an entry.
- The unit does not support some characters.
 If a copied entry includes those characters, they are replaced with other available characters or "*".
- If you receive a call while copying phonebook entries, the copying procedure stops. Try again after finishing the call.

Setting conversion codes

You must first set the following 3 dialing codes before transferring the phonebook from your cellular phone (each 4 digits max.).

- "International code": An international prefix used when you make an international call.
- "Country code": Your country code for international calls.

 "Trunk prefix": A trunk prefix; the initial digit(s) to be dialed in a domestic call, prior to the area code.

Handset

- 1 (MENU)
- 2 To store "International code": #1117

To store "Country code": #1118 To store "Trunk prefix": #119

- Enter the desired number. \rightarrow [SAVE]
- [OFF]

Note:

 After you copy the entries, confirm that the numbers were transferred correctly.

Link to Cell app

For Android™ users

The free Link to Cell app helps you integrate your Android phone with your DECT phone for convenient use.

Important:

- Your cellular phone must support SPP (Serial Port Profile) specification.
- Application (App) Alerts On/Off This feature alerts your DECT phone when your paired Android phone receives the following alert information:
 - [Google Calendar]™
 - [Email]
 - [Gmail1™
 - [Text messages]
 - [Facebook]
 - [Twitter]
 - [Instagram]
 - [Low Battery] information

You can turn each type of alert on or off using the Link to Cell app. If you turn the alerting app on, your DECT phone alerts you with the corresponding information.

■ Phone Settings

Using your paired Android phone, you can program your Phone Settings for the following features:

- ITime adjustment1*1
- [Cell line only mode] (page 18)
- International codel. [Country codel. and [Trunk prefix] (page 57)
- *1 When your paired Android phone is within the base unit's range, the date and time information is updated on the handset and base unit's display, if time adjustment feature is activated on your Android phone.

Installing the Link to Cell app

Download links are also available at the web page below.



www.panasonic.net/pcc/support/tel/ appalerts



Starting the app for the first time

- Make sure that your Android device's Bluetooth feature is turned on and that your Android device is paired to the base
- Start the Link to Cell app by tapping its
- Follow the on-screen instructions.

Important:

- For further information, refer to the instructions on web page listed above.
- To use this feature, the following settings are required.

- Android phone: Bluetooth must be turned on.
- Android phone: [Application Alerts manager]*1 must be turned on.
- Handset or base unit: "Alert On/ off" must be turned on (page 59).
- If this feature does not work, turn on your device's Bluetooth feature, unplug the base unit's AC adaptor, and then reconnect it.

*1 Turning on [Application Alerts managerl

Use the following procedure after installing the Link to Cell app. Android 2.x: Open your device's [Settings] app. → Tap [Accessibility]. → Turn on the [Accessibility] and

[Application Alerts manager] checkboxes. Android 4.x: Open your device's

[Settings] app. → Tap [Accessibility]. → Turn on [Application Alerts managerl.

Requirements

An Android device (Android 2.1 or later)

Text message (SMS) alert

For iPhone and BlackBerry® users

This feature alerts you on your DECT phone when your paired cellular phone receives SMS messages. The Link to Cell app is not required for iPhone and BlackBerry users.

Important:

- Your cellular phone must support MAP (Message Access Profile) specification.
- For further information, refer to the instructions on web page listed below: www.panasonic.net/pcc/support/tel/sms/
- To use this feature, the following settings are required:
 - iPhone and BlackBerry Phone: Bluetooth must be turned on.
 - Handset or base unit: "Alert On/ off" must be turned on (page 59).

 If this feature does not work, turn on your device's Bluetooth feature, unplug the base unit's AC adaptor, and then reconnect it.

Alert settings for your DECT phone

If your cellular phone is paired to the base unit and receives notifications, the handset and/or base unit can alert you:

- by briefly displaying a message
- by announcement
- by sounding alert tones

Important:

• For Android users: Use the Link to Cell app to enable the desired alerts (page 58).

Turning alert on/off

Once this feature is turned on, it will alert you on the handset and base unit when your cellular phone receives notifications.

- "On" (default): The handset and/or base unit alert you.
- "off": The handset and/or base unit do not alert you.

You can configure this setting using either the base unit or one of the handsets.

Handset / Base unit

- For CELL 1: [MENU]#6101 For CELL 2: [MENU]#6102
- [♠]: Select the desired setting. → [SAVE]
- Proceed with the operation for your unit. Handset: [OFF] Base unit: [EXIT]

Note:

• In step 1, you can also enter the "Alert settings" menu by pressing and holding [APP ALERTS] on the base unit.

Setting the voice alert

You can turn on/off the voice alert.

 "on" (default): The handset and/or base unit notify you by voice announcement.

 "Off": Voice announcement is not available as alert.

You can configure this setting using either the base unit or one of the handsets.

Handset / Base unit

- 1 For CELL 1: [MENU]#6031 For CELL 2: [MENU]#6032
- 2 [♠]: Select the desired setting. → [SAVE]
- 3 Proceed with the operation for your unit. Handset: [OFF] Base unit: [EXIT]

Selecting the alert tone

Handset

- 1 For CELL 1: (MENU)#6041 For CELL 2: (MENU)#6042
- 2 (*): Select the desired setting.
- 3 [SAVE] \rightarrow [OFF]

Temporary alert off

You can temporarily disable the alerts by pressing **[APP ALERTS]**.

Base unit

Press [APP ALERTS] to temporarily disable alerts.

- APP is displayed.
- To enable alerts again, press [APP ALERTS] again.

Using a Bluetooth wireless headset (optional) for landline calls

By pairing a Bluetooth headset to the base unit, you can have a hands-free conversation wirelessly for landline calls.

Important:

- Your Bluetooth wireless headset must support the HeadSet Profile (HSP) specification.
- 1 headset can be paired to the base unit.

- Only 2 Bluetooth devices can be used with the unit at the same time (for example, 2 cellular lines, or the headset and 1 cellular line).
- For best performance, we recommend using a Bluetooth headset within 1 m (3.3 feet) of the base unit. A headset can communicate with the base unit within a range of approximately 10 m (33 feet).

Pairing a headset to the base unit

Important:

- Make sure that the Bluetooth headset is not connected to any other Bluetooth device.
- 1 Your headset:
 - Set your headset to pairing mode.Refer to the headset operating
- instructions.

 2 Handset:
- (MENU)#621
- If your headset PIN is "0000", go to step 4.

If your headset PIN is other than "0000", press [CLEAR], then enter your headset PIN.

- Typically, default PIN is "0000". Refer to the headset operating instructions.
- 4 Press [OK], then wait until a long beep sounds.
- 5 [OFF]
 - When **SQ** is displayed on the base unit, the headset is available for use.

Connecting/disconnecting a headset

If you cannot connect the headset and base unit using the headset, you can connect using the handset.

To use your headset with another Bluetooth device such as a cellular phone, you may need to disconnect it from the base unit.

Important:

Make sure that the headset is turned on.

Handset

1 To connect/disconnect: [MENU]#622

A long beep sounds.

2 [OFF]

Unpairing a headset

You can cancel a pairing of the headset that is stored to the base unit.

Handset

- 1 (MENU)#612
- 2 [♣]: "Yes" → [SELECT]
 - When the headset is unpaired, the C disappears from the base unit display.
- 3 [OFF]

Operating a Bluetooth wireless headset using a landline

Important:

 Refer to your headset operating instructions for headset operations.

Answering landline calls with your headset

To answer a landline call, press your headset's button referring to your headset operating instructions.

When you finish talking, press your headset's button referring to your headset operating instructions.

Note:

 If you cannot hang up the call using your headset, press [♣] on the base unit 2 times.

Switching between the base unit and vour headset

You can switch between the base unit and your headset:

- during a landline call with the base unit speakerphone.
- during an intercom call between the base unit and handset.
- while listening to messages recorded on the base unit answering system.

■ To switch to your headset: Press [] on the base unit.

■ To switch to the base unit: Press [♣] on the base unit.

Call sharing between your headset and the handset

Important:

- To activate this feature, you should set privacy mode to off beforehand (page 45).
- While the handset is on a landline call:

 To join the conversation with your headset, press your headset's button referring to your headset operating instructions.
- While your headset is on a landline call:

 To join the conversation with the handset, press [].

Adjusting your headset receiver volume

Base unit

Press [▲] or [▼] repeatedly while using your headset.

Note:

 Depending on your headset, the receiver volume may not be adjustable.

Answering system for landline

The answering system can answer and record calls for you when you are unavailable to answer the phone.

You can also set the unit to play a greeting message but not to record caller messages by selecting "Greeting only" as the recording time setting (page 68).

Important:

 Make sure the unit's date and time setting. is correct (page 15).

Memory capacity (including your greeting message)

The total recording capacity is about 16 minutes. A maximum of 64 messages can be recorded.

Note:

- When message memory becomes full:
 - "Messages full" is shown on the handset and base unit display.
 - The ANSWER ON/OFF indicator on the base unit flashes rapidly if the answering system is turned on.
 - If you use the pre-recorded greeting message, the unit automatically switches to another pre-recorded greeting message asking callers to call again later.
 - If you recorded your own greeting message, the same message is still announced to callers even though their messages are not recorded.

Turning the answering system on/off

Base unit

Press [ANSWER ON/OFF] to turn on/off the answering system.

Handset

To turn on: (MENU)#327 To turn off: [MENU]#328

[OFF]

Note for base unit and handset:

 When the answering system is turned on. the ANSWER ON/OFF indicator on the base unit lights up.

Greeting message

When the unit answers a call, a greeting message is played to callers. You can use either:

- your own greeting message
- a pre-recorded greeting message

Recording your greeting message

Handset

- 1 (MENU)#302
- 2 [♠]: "Yes" → [SELECT]
- After a beep sounds, hold the handset about 20 cm (8 inches) away and speak clearly into the microphone (2 minutes max.).
- Press **(STOP)** to stop recording. → [OFF]

Using a pre-recorded greeting message

The unit provides 2 pre-recorded greeting messages:

- If you reset to pre-recorded greeting or do not record your own greeting message, the unit plays a pre-recorded greeting asking callers to leave a message.
- If the message recording time (page 68) is set to "Greeting only", callers' messages are not recorded and the unit plays a different pre-recorded greeting message asking callers to call again.

Resetting to a pre-recorded greeting message

If you change into a pre-recorded greeting message once you record your own greeting message, your own recorded greeting message is erased.

Handset

- 1 (MENU)#304
- 2 [YES] → [OFF]

Playing back the greeting message

Handset

- 1 (MENU)#303
- 2 To exit, press [OFF].

Listening to messages

Important:

- If your phone service provider offers voicemail service, the voicemail service may answer calls before the base unit's built-in answering system has a chance to answer calls and record messages. In this case, messages you expect to be recorded by the answering system will be recorded on the voicemail service. For more information, see "For landline voicemail service subscribers" (page 68).
- When using the base unit or handset to listen to messages, the noise reduction feature (page 22) is activated automatically in spite of the setting (NR is not displayed).

Using the base unit

When new messages have been recorded:

- [►■] on the base unit flashes.
- "New message" is displayed.Press [►■] (PLAY).
- During playback, [►■] on the base unit lights.

- If new messages have been recorded, the base unit plays back new messages.
- If there are no new messages, the base unit plays back all messages.

Operating the answering system during playback

Key	Operation
[▲] or [▼]	Adjust the speaker volume
[144]	Repeat message*1
[>> 1]	Skip message
[PAUSE]	Pause message. To resume playback, press [►■].
[►■] (STOP)	Stop playback
[ERASE]	Erase currently playing message

*1 If pressed within the first 5 seconds of a message, the previous message is played.

Calling back (Call Display subscribers only)

■ Using a landline:

Press [♣] during playback.

- To edit the number before calling back, press [EDIT] repeatedly until the phone number is shown in the desired format (page 55).
- Using a cellular line:

Press [CELL 1] or [CELL 2] during playback. To edit the number before calling back, press [EDIT] repeatedly until the phone number is shown in the desired format (page 55).

Erasing all messages

Press [ERASE] 2 times while the unit is not in use

Using the handset

When new messages have been recorded, "New message" is displayed.

- 1 To listen to new messages: [MENU]#323
 To listen to all messages: [MENU]#31214
- 2 When finished, press [OFF].

Note:

- To switch to the receiver, press [].
- You can also use the [PLAY] soft key, if displayed, to play new messages.

Operating the answering system [MENU] \rightarrow [\diamondsuit]: "Answering device" \rightarrow [SELECT]

Key	Operation
[▲] or [▼]	Adjust the receiver/speaker volume (during playback)
1 or [◄]	Repeat message (during playback)*1
2 or [►]	Skip message (during playback)
3	Enter the "Settings" menu
4	Play new messages
5	Play all messages
6	Play greeting message
76	Record greeting message
8	Turn answering system on
[PAUSE]	Pause message*2
9 or [STOP]	Stop recording Stop playback
0	Turn answering system off
¥ 4*3	Erase currently playing message
* 5	Erase all messages
× 6	Reset to a pre-recorded greeting message

- *1 If pressed within the first 5 seconds of a message, the previous message is played.
- *2 To resume playback:
 - [♣]: "Playback" → [SELECT]
- *3 You can also erase as follows:

[PAUSE] \rightarrow [♣]: "Erase" \rightarrow [SELECT] \rightarrow [♣]: "Yes" \rightarrow [SELECT]

Calling back (Call Display subscribers only)

- Using a landline:
 - 1 Press [PAUSE] during playback.
 - 2 [♣]: "Call back" → [SELECT]
- Using a cellular line:
 - 1 Press [PAUSE] during playback.
 - [[♣]: "Call back (Cell)" →
 [SELECT]
 - The unit starts dialing when:
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).
 - 3 [♣]: Select the desired cellular phone.→ [SELECT]

Editing the number before calling back

- Using a landline:
- 1 Press (PAUSE) during playback.
- 2 [♣]: "Edit & Call" → [SELECT]
- 3 Press [EDIT] repeatedly until the phone number is shown in the desired format (page 55).
- 4 []
- Using a cellular line:
- 1 Press [PAUSE] during playback.
- 2 (♣): "Edit & Call" → [SELECT]
- 3 Press [EDIT] repeatedly until the phone number is shown in the desired format (page 55).
- 4 [CELL]
 - The unit starts dialing when:
 - only 1 cellular phone is paired.
 - a specific line is set to make cellular calls (page 19).
- 5 [♠]: Select the desired cellular phone. → [SELECT]

Erasing all messages

1 (MENU)#325

For assistance, visit www.panasonic.ca/english/support

64

Advanced new message alerting features

Audible message alert

This feature allows the base unit to beep to inform you of a new message arrival when new messages are recorded. The base unit beeps 2 times every minute until you listen to the messages, if the "Base unit beep" setting is turned on. The default setting is "Off".

Handset

- 1 (MENU)#339
- 2 [♣]: Select the desired setting. → [SAVE] → [OFF]

New message alert by a call

This feature allows you to receive a notification by phone when new messages are recorded. The base unit calls a phone number you specify. You can then operate the answering system remotely to listen to the new message.

To use this feature, you must:

- store a phone number to which the unit makes the call to.
- turn on the new message alert setting.
 After you answer the new message alert call, you can listen to messages from that call (page 66).

This feature is only available for landline.

Important:

 A new message alert is stopped 1 minute after the unit starts to call. The unit will not retry the call even if the call is not answered.

Storing a phone number to which the unit makes an alert call

Handset

- From the phonebook:
 - 1 [MENU]#338

 - 3 [♣]: "Phonebook" → [SELECT]
 - **4** [♣]: Select the desired phonebook entry. → [SAVE] → [OFF]
- By entering a phone number:
 - 1 (MENU)#338
 - 2 [♠]: "Notification to" →
 [SELECT] → [ADD]
 - 3 [♠]: "Manual" → [SELECT]
 - Enter the desired name (16 characters max.). → [OK]
 - 5 Enter the desired number (24 digits max.). → [OK] → [SELECT] → [OFF]

Turning on/off the new message alert setting

Handset

- 1 (MENU)#338
- 2 [♣]: "On/Off" → [SELECT]
- 3 [♠]: Select the desired setting. → [SAVE] → [OFF]

Editing the set phone number

Handset

- 1 [MENU]#338
- 2 (♣): "Notification to" → [SELECT]
- 3 [MENU] \rightarrow [\diamondsuit]: "Edit" \rightarrow [SELECT]
- 4 Edit the name if necessary (16 characters max.). → [OK]
- 5 Edit the phone number if necessary (24 digits max.). → [OK] → [SELECT] → [OFF]

Erasing the set phone number

Handset

- 1 [MENU]#338
- 2 [♣]: "Notification to" → [SELECT]
- 3 [MENU] \rightarrow [\updownarrow]: "Erase" \rightarrow [SELECT]
- 4 (♠): "Yes" → [SELECT] → [OFF]
 - The new message alert setting is turned off.

Activating/inactivating the remote access code to play messages

If you activate this feature, you must enter the remote access code (page 66) to play the new message from the new message alert call. This is so that unauthorized parties cannot listen to your messages. The default setting is "Inactivate".

- "Inactivate": You can listen to the message by pressing 4 to play new messages (without entering the remote access code).
- "Activate": You must enter your remote access code and then press 4 to play new message.

Handset

- 1 (MENU)#338
- 2 (♣): "Remote code" → [SELECT]
- 3 [♣]: Select the desired setting. → [SAVE] → [OFF]

Listening to messages

After you answer the new message alert, you can listen to the messages as follows.

■ When the remote access code is set to "Inactivate":

Press 4 to play the new message during the announcement.

- When the remote access code is set to "Activate":
 - Enter the remote access code (page 66) during the announcement.
 - 2 Press 4 to play the new message.

Note:

- Within 10 seconds after listening to new messages, you can press # 9 during the call to turn off the new message alert by a call feature.
- Even if the unit makes a new message alert call, the handset redial list does not show the record. However, on the base unit redial list it is shown as "Message alert".

Remote operation

Using a touch-tone phone, you can call your phone number from outside and access the unit to listen to messages or change answering system settings. The unit's voice guidance prompts you to press certain dial keys to perform different operations.

Remote access code

A 3-digit remote access code must be entered when operating the answering system remotely. This code prevents unauthorized parties from listening to your messages remotely. The default setting is "111".

Important:

 To prevent unauthorized access to this product, we recommend that you regularly change the remote code.

Handset

- 1 (MENU)#306
- **2** Enter the desired 3-digit remote access code.
- 3 [SAVE] \rightarrow [OFF]

Deactivating remote operation

Press ★ in step 2 on "Remote access code", page 66.

The entered remote access code is deleted.

Using the answering system remotely

- Dial your landline phone number from a touch-tone phone.
- After the greeting message starts, enter vour remote access code.
- Follow the voice guidance prompts as necessary or control the unit using remote commands (page 67).
- When finished, hang up.

Voice guidance

During remote operation, the unit's voice quidance starts and prompts you to press 1 to perform a specific operation, or press 2 to listen to more available operations.

Note:

 If you do not press any dial keys within 10 seconds after a voice guidance prompt, the unit disconnects your call.

Remote commands

You can press dial keys to access certain answering system functions without waiting for the voice guidance to prompt you.

Key	Operation
1	Repeat message (during playback)*1
2	Skip message (during playback)
4	Play new messages
5	Play all messages
9	Stop playback
0	Turn answering system off
* 4	Erase currently playing message
* 5	Erase all messages
* #	End remote operation (or hang up)

If pressed within the first 5 seconds of a message, the previous message is played.

Turning on the answering system remotely

- Dial your phone number from a touch-tone phone.
- Let the phone ring 15 times. A long beep is heard.
- Enter your remote access code within 10 seconds after the long beep.
 - The greeting message is played back.
 - You can either hang up, or enter your remote access code again and begin remote operation (page 66).

Answering system settings

Call screening

Handset / Base unit

While a caller is leaving a message, you can listen to the call through the unit's speaker. To adjust the speaker volume, press [A] or ▼ repeatedly.

You can answer the call by pressing [] on the handset or [] on the base unit. Call screening can be set for each unit. The default setting is "on".

- [MENU]#310
- [♠]: Select the desired setting. → [SAVE]
- Proceed with the operation for your unit. Handset: [OFF] Base unit: [EXIT]

Number of rings before the unit answers a call

You can change the number of times the phone rings "Ring count" before the unit answers calls. You can select 2 to 7 rings, or "Toll saver".

The default setting is "4 rings".

"Toll saver": The unit's answering system answers at the end of the 2nd ring when new messages have been recorded, or at the end of the 5th ring when there are no new messages. If you call your phone from outside to listen to new messages (page 67), you know that there are no new messages when the phone rings for the 3rd time. You can then hang up without being charged for the call.

Handset

- (MENU)#211
- [♠]: Select the desired setting. → $[SAVE] \rightarrow [OFF]$

For landline voicemail service subscribers

If you subscribe to a flat-rate service package that includes Call Display, Call Waiting, voicemail, and unlimited local/regional/long distance calls, please note the following:

- To use the voicemail service provided by your phone service provider rather than the unit's answering system, turn off the answering system (page 62).
- To use this unit's answering system rather than the voicemail service provided by your phone service provider, please contact your phone service provider to deactivate your voicemail service.

If your phone service provider cannot do this:

- Set this unit's "Ring count" setting so that this unit's answering system answers calls before the voicemail service of your phone service provider does. It is necessary to check the number of rings required to activate the voicemail service provided by your phone service provider before changing this settina.
- Change the number of rings of the voicemail service so that the answering system can answer the call first. To do so, contact your phone service provider.

Caller's recording time

You can change the maximum message recording time allowed for each caller. The default setting is "3 min".

Handset

- 1 [MENU]#305
- [♠]: Select the desired setting. → SAVE] → [OFF]

Selecting "Greeting only"

You can select "Greeting only" which sets the unit to announce a greeting message to callers but not record messages. Select "Greeting only" in step 2 on "Caller's recording time", page 68.

Note:

- When you select "Greeting only":
 - If you do not record your own message, the unit will play the pre-recorded greeting-only message asking callers to call again later.
 - If you use your own message, record the greeting-only message asking callers to call again later (page 62).

Voicemail service for landline

Voicemail is an automatic answering service offered by your phone service provider. After you subscribe to this service, your phone service provider's voicemail system answers calls for you when you are unavailable to answer the phone or when your line is busy. Messages are recorded by your phone service provider, not your telephone. Please contact your phone service provider for details of this service.

Important:

 To use the voicemail service provided by your phone service provider rather than the unit's answering system, turn off the answering system (page 62). For details, see page 68.

Storing the voicemail (VM) access number

In order to listen to your voicemail messages, you must dial your phone service provider's voicemail access number. Once you have stored your voicemail access number, you can dial it automatically (page 70).


Handset

- 1 (MENU)#331
- 2 Enter your access number (24 digits max.). → [SAVE] → [OFF]

Note:

 When storing your voicemail access number and your mailbox password, press [A] (Pause) to add pauses (page 21) between the access number and the password as necessary. Contact your phone service provider for the required pause time.

Example:



To erase the voicemail access number

Handset

- 1 (MENU)#331
- 2 Press and hold [CLEAR] until all digits are erased. → [SAVE] → [OFF]

Voicemail (VM) tone detection

Handset / Base unit

Your phone service provider sends special signals (sometimes called "voicemail tones" or "stutter tones") to the unit to let you know you have new voicemail messages. If you hear a series of dial tones followed by a continuous dial tone after you press [) on the handset or press [) on the base unit, you have new voicemail messages. Soon after you hang up a call or after the phone stops ringing, your unit checks the phone line to see if new voicemail messages have been recorded.

Turn this feature off when:

- You do not subscribe to voicemail service.
- Your phone service provider does not send voicemail tones.
- Your phone is connected to a PBX.
 If you are not sure which setting is required, contact your phone service provider.

Turning VM tone detection on/off

The default setting is "on".

Handset

- 1 [MENU]#332
- 2 [♣]: Select the desired setting. → [SAVE] → [OFF]

Listening to voicemail messages

When new messages have been recorded, "Voicemail msg. via phone co."*1/ "Voicemail msg."*2 are displayed if message indication service is available.

- Handset
- *2 Base unit

Handset

- [MENU]#330
 - The speakerphone turns on.
- 2 Follow the pre-recorded instructions.
- 3 When finished, hang up.

 You can also use the [ACCESS] soft key, if displayed, to play new voicemail messages.

Base unit

To listen to voicemail messages, you have to dial your voicemail access number manually.

Note for handset and base unit:

 If the handset and base unit still indicate there are new messages even after you have listened to all new messages, turn it off by pressing and holding # until the handset or base unit beeps.

Wall mounting


The base unit can be mounted on a wall by changing the wall mounting adaptor's position.

Note:


 Make sure that the wall and the fixing method are strong enough to support the weight of the unit.

Base unit


To remove the wall mounting adaptor, push down the release levers (1). Remove the adaptor (2).



- 1) Turn the adaptor so that the words "UP WALL" are facing up.
 - (2) Tuck the telephone line cord inside the wall mounting adaptor.
 - (3) Connect the AC adaptor cord and telephone line cord.
 - A Hook




- 3 Insert the lower tabs of the adaptor into the unit's bottom slots (1), then insert by pushing down the levers of the adaptor into the upper slots (2).
 - The words "UP WALL" should be facing up.



- 4 Mount the unit on a wall then slide down to secure in place.
 - This product is compliant with the following wall phone plate sizes (2 types).
 - **A** 83 mm (3 ¹/₄ inches)
 - **(**4 inches)

Fit the slots of the unit onto the corresponding wall phone plate tabs for (**②**) and (**①**) respectively.



Charger

Drive the screws (**A**) (not supplied) into the wall.

B 27.2 mm (1 ¹/₁₆ inches)



Error messages

Display message	Cause/solution
Ask phone company for VM access #	You have not stored the voicemail access number. Store the number (page 69).
Base no power Of No link. Re- connect base AC adaptor. Of No link.	Confirm the base unit's AC adaptor is connected to the unit and the power outlet correctly. The handset has lost communication with the base unit. Move closer to the base unit and try again. Unplug the base unit's AC adaptor to reset the unit. Reconnect the adaptor and try again. The handset's registration may have been cancelled. Re-register the handset (page 52). When "No link." is displayed during a power failure, place a handset on the base unit to supply power to the base unit.
Busy	 No cellular phone is paired to the base unit. Pair a cellular phone (page 16). The called unit is in use. Other units are in use and the system is busy. Try again later. The handset you are using is too far from the base unit. Move closer and try again. Only 2 Bluetooth devices can be used with the unit at the same time (for example, 2 cellular lines, or the headset and 1 cellular line).
Check tel line	The supplied telephone line cord has not been connected yet or not connected properly. Check the connections (page 10). If you do not connect the telephone line cord and use only cellular lines, set the cellular line only mode (page 18).
Error!!	Recording was too short. Try again. Someone is using a cellular line or headset. Try again later. The phonebook copy is incomplete (page 57). The cellular phone is disconnected from the base unit. Make sure that other Bluetooth devices are not connected to the cellular phone, and try again.
Failed	Although the unit tried to connect to the cellular phone or headset, the connection has been failed. Someone is using a cellular line or headset. Try again later. Make sure that the cellular phone or headset is not connected to other Bluetooth devices.

For assistance, visit www.panasonic.ca/english/support

72

Display message	Cause/solution
Invalid	 There is no handset registered to the base unit matching the handset number you entered. The handset is not registered to the base unit. Register the handset (page 52).
Requires subscription to Caller ID.	You must subscribe to a Call Display service. Once you receive caller information after subscribing to a Call Display service, this message will not be displayed.
Use rechargeable battery.	A wrong type of battery such as alkaline or manganese was inserted. Use only the rechargeable Ni-MH batteries noted on page 4, 7.

Troubleshooting

If you still have difficulties after following the instructions in this section, disconnect the base unit's AC adaptor, then reconnect the base unit's AC adaptor. Remove the batteries from the handset, and then insert them into the handset again.

General use

Problem	Cause/solution
The handset does not turn on even after installing charged batteries.	Place the handset on the base unit or charger to turn on the handset.
The unit does not work.	 Make sure the batteries are installed correctly (page 10). Fully charge the batteries (page 11). Check the connections (page 10). Unplug the base unit's AC adaptor to reset the unit. Reconnect the adaptor and try again. The handset has not been registered to the base unit. Register the handset (page 52).

Problem	Cause/solution
I cannot pair a cellular phone to the base unit.	Depending on the compatibility of the cellular phone, you may not be able to pair it to the base unit. Confirm that your cellular phone supports the hands-free profile (HFP) specification. Confirm that the Bluetooth feature of your cellular phone is turned on. You may need to turn this feature on depending on your cellular phone. The Bluetooth technology on your cellular phone may not be functioning normally. Turn off and on your cellular phone. If your cellular phone is already connected to another Bluetooth device such as a Bluetooth headset, turn it off or disconnect it from your cellular phone. Some cellular phones may require you to enter the Bluetooth PIN to pairing. Confirm that you entered the correct PIN.
I cannot connect a cellular phone to the base unit.	Confirm that your cellular phone is turned on. Confirm that your cellular phone is within base unit range (page 13). Your cellular phone's Bluetooth feature is turned off. Turn it on. Depending on the state of the wireless environment, such as the presence of any electrical interference, there may be a delay even if the auto connection feature is turned on. You can connect to the base unit manually (page 18). The cellular phone has not been paired to the base unit. Pair the cellular phone (page 16). If your cellular phone is already connected to another Bluetooth device such as a Bluetooth headset or other Panasonic DECT phone, disconnect the device, then perform the connecting procedure to the base unit. If your cellular phone is already registered on another Panasonic DECT phone, this function will not work properly. We strongly recommend that you remove the registration of this phone on both your cellular phone and on the other Panasonic DECT phone.
I cannot hear a dial tone.	 Make sure that the CELL indicator lights up (page 14). The base unit's AC adaptor or telephone line cord is not connected. Check the connections. Disconnect the base unit from the telephone line and connect the line to a known working telephone. If the working telephone operates properly, contact our service personnel to have the unit repaired. If the working telephone does not operate properly, contact your phone service provider.
The base unit beeps.	New messages have been recorded. Listen to the new messages (page 63).

For assistance, visit www.panasonic.ca/english/support

Menu list

Problem	Cause/solution
The display is in a language I cannot read.	Change the display language (page 15).
I cannot register a handset to a base unit.	 The maximum number of handsets (6) is already registered to the base unit. Cancel unused handset registrations from the base unit (page 52).

Battery recharge

Problem	Cause/solution
The handset beeps and/or a flashes.	Battery charge is low. Fully charge the batteries (page 11).
I fully charged the batteries, but - still flashes, - is displayed, or - the operating time seems to be shorter.	 Clean the battery ends (⊕, ⊕) and the charge contacts with a dry cloth and charge again. It is time to replace the batteries (page 10).

Making/answering calls, intercom

Problem	Cause/solution
y is displayed.	 The handset is too far from the base unit. Move closer. The base unit's AC adaptor is not properly connected. Reconnect AC adaptor to the base unit. The handset is not registered to the base unit. Register it (page 52).
Noise is heard, sound cuts in and out.	You are using the handset or base unit in an area with high electrical interference. Re-position the base unit and use the handset away from sources of interference. Move closer to the base unit. If you use a DSL/ADSL service, we recommend connecting a DSL/ADSL filter between the base unit and the telephone line jack. Contact your DSL/ADSL provider for details.
The handset or base unit does not ring.	 The ringer volume for landline is turned off. Adjust the ringer volume (page 21, 27, 43, 47). The ringer volume for cellular line is turned off. Adjust the ringer volume (page 21, 27, 41, 46). The unit which is not selected to ring for cellular calls does not ring. To change the selection, see page 17. Night mode is turned on. Turn it off (page 49).
I cannot make local calls with the handset or base unit using a cellular line.	You need to add your area code when making cellular calls. Store your area code in order to automatically add it to the beginning of the 7-digit phone number when making cellular calls (page 19).

Problem	Cause/solution
I cannot make or answer cellular calls with the handset or base unit.	 Depending on the cellular phone's compatibility (page 4), you may not be able to make or answer cellular calls even if the cellular phone is connected to the base unit. Make sure that the CELL indicator lights up and the cellular phone is connected to the base unit (page 18). Only 2 Bluetooth devices can be used with the unit at the same time (for example, 2 cellular lines, or the headset and 1 cellular line). The cellular phone is being used separately from your system.
I can make and answer cellular calls but cannot hear a sound.	 The Bluetooth technology on your cellular phone may not be functioning normally. Turn off and on your cellular phone. Disconnect and reconnect the base unit AC adaptor and try again.
I cannot switch cellular calls from the unit to the cellular phone.	Your cellular phone may not support this feature. Refer to the operating instructions of your cellular phone.
I cannot make a call using a landline.	The dialing mode may be set incorrectly. Change the setting (page 15).
I cannot use a cellular line or a landline.	The unit can be used to talk on 2 lines at the same time (for example, 2 cellular lines, or the landline and 1 cellular line).
I cannot make long distance calls.	Make sure that you have long distance service.

Call Display/Talking Call Display

Problem	Cause/solution
Caller information is not displayed.	You must subscribe to Call Display service. Contact your phone service provider for details. If your unit is connected to any additional telephone equipment such as a Call Display box or cordless telephone line jack, plug the unit directly into the wall jack. If you use a DSL/ADSL service, we recommend connecting a DSL/ADSL filter between the base unit and the telephone line jack. Contact your DSL/ADSL provider for details. The name display service for landline calls may not be available in some areas. Contact your phone service provider for details. Other telephone equipment may be interfering with this unit. Disconnect the other equipment and try again.
Caller information is displayed or announced late.	 Depending on your phone service provider, the unit may display or announce the caller's information at the 2nd ring or later. Move closer to the base unit.

For assistance, visit www.panasonic.ca/english/support

Problem	Cause/solution
Caller information is not announced.	 The ringer volume for landline is turned off. Adjust the ringer volume (page 43, 47). The ringer volume for cellular line is turned off. Adjust the ringer volume (page 41, 46). The unit which is not selected to ring for cellular calls does not announce caller information. To change the selection, see page 17. The Talking Call Display feature is turned off. Turn it on (page 43, 47). The ring as cell mode is set to "on (without Talking CID)". To change the mode, see page 17. The number of rings for the answering system is set to "2 rings" or "Toll saver". Select a different setting (page 67). Your unit does not announce caller information while the other devices such as headset or handsets are engaged in a call.
I cannot dial the phone number edited in the caller list.	The phone number you dialed might have been edited incorrectly (for example, the long distance "1" or the area code is missing). Edit the phone number with another pattern (page 55).
Time on the unit has shifted.	 Incorrect time information from incoming Call Display changes the time. Set the time adjustment to "Manual" (off) (page 43).
The 2nd caller's information is not displayed during an outside call. (Visual Call Waiting feature does not function.)	• In order to use Call Display, Call Waiting, or Visual Call Waiting, you must first contact your phone service provider and subscribe to the desired service. After subscribing, you may need to contact your phone service provider again to activate this specific service, even if you already subscribed to both Call Display and Visual Call Waiting services.

Using Bluetooth devices

Problem	Cause/solution
I cannot copy phonebook entries from a cellular phone.	Confirm that the cellular phone supports Bluetooth wireless technology. Confirm that the cellular phone supports the Phone Book Access Profile (PBAP) or Object Push Profile (OPP) specification. If the cellular phone is already connected to another Bluetooth device such as a Bluetooth headset, turn it off or disconnect it from the cellular phone. Someone is using a cellular line or headset. Try again later. Turn the cellular phone off, then turn it on and try again. If an entry is already stored in the unit's phonebook, the entry cannot be copied even by selecting another group. iPhone does not support individual phonebook copy.
I cannot have a conversation using the headset. or I cannot connect my headset to the base unit.	Confirm that the Bluetooth wireless headset supports the HeadSet Profile (HSP) specification. Your Bluetooth headset is not paired. Pair it (page 60). Turn your headset off, then turn it on and try again. If your headset is already connected to another Bluetooth device such as your cellular phone, disconnect the headset from your cellular phone, then perform the connecting procedure from the base unit. Only 2 Bluetooth devices can be used with the unit at the same time (for example, 2 cellular lines, or the headset and 1 cellular line).
Noise is heard during a call on the headset.	A Bluetooth headset can communicate with the base unit within a range of approximately 10 m (33 feet). The connection may be subject to interference from obstructions such as walls or electronic devices. Move closer to the base unit.
Some headset enhanced features are not available.	The base unit does not support enhanced features such as Last number redial or Call reject.
An error tone is heard when I try to program the Bluetooth feature.	The Bluetooth feature cannot be accessed immediately after connecting the AC adaptor to the base unit. Wait a few seconds and try again. The headset has not connected to the base unit yet, even though you performed the connecting procedure setting. Wait a few seconds and try again.

Problem	Cause/solution
App alert is not displayed or announced. or Text message alert is not displayed or announced.	Confirm that the cellular phone supports the Message Access Profile (MAP) specification to use text message alert feature. Confirm that the cellular phone supports the Serial Port Profile (SPP) specification to use App alert feature. Confirm that the [Application Alerts manager] setting of your Android phone is turned on. "Alert On/Off" is set to "Off". Set it to "On" (page 59). "Voice alert" is set to "Off". Set it to "On" (page 59). The Bluetooth device's Bluetooth notifications setting is turned off. The handset selected to display and/or announce alerts is in use. The Bluetooth device or its corresponding cellular line is in use. The alert feature is temporarily off. Press [APP ALERTS] on the base unit. Your cellular phone's Bluetooth feature is turned off. Turn it on.

Answering system

Problem	Cause/solution
The unit does not record new messages.	The answering system is turned off. Turn it on (page 62). The answering system does not answer or record calls from cellular lines. The message memory is full. Erase unnecessary messages (page 63, 64). The recording time is set to "Greeting only". Change the setting (page 68). Your phone service provider's voicemail service may be answering your calls before the unit's answering system can answer your calls. Change the unit's number of rings setting (page 67) to a lower value, or contact your phone service provider. The answering system will not answer incoming calls while the other devices such as headset or handsets are engaged in a call.
I cannot operate the answering system remotely.	The remote access code is not set. Set the remote access code (page 66). You are entering the wrong remote access code. If you have forgotten your remote access code, enter the remote access code setting to check your current code (page 66). The answering system is turned off. Turn it on (page 67). You cannot operate the answering system when calling a cellular phone paired to the base unit.

Problem	Cause/solution
The unit does not emit the specified number of rings.	 If the ring once setting is turned off (page 33), the number of rings decreases by 1 from the specified number of rings.

Bluetooth PIN

Problem	Cause/solution	
I cannot remember the PIN.	Change the PIN using the following method. Handset:	
	1 [MENU]#619	
	2 *7000	
	3 Enter the new 4-digit PIN. → [OK]	
4	4 Enter the new 4-digit PIN again. → [SAVE] → [OFF]	

Voicemail

Problem	Cause/solution
"Voicemail msg. via phone co." is shown on the handset display. or "Voicemail msg." is shown on the base unit display. How do I remove this message from the display?	This notification is displayed when your phone service provider's voicemail service (not the unit's answering system) has recorded a message for you. Typically you can remove this notification from the display by listening to the message. To listen to the message, dial the voicemail number provided by your phone service provider (for most cases, this will be your own phone number), and follow the voice instructions. Depending on your phone service provider, you may need to remove all messages from your voice mailbox to remove the notification. You can also remove this notification by pressing and holding # until the unit beeps.

Liquid damage

Problem	Cause/solution
Liquid or other form of moisture has entered the handset/base unit.	Disconnect the AC adaptor and telephone line cord from the base unit. Remove the batteries from the handset and leave to dry for at least 3 days. After the handset/base unit are completely dry, reconnect the AC adaptor and telephone line cord. Insert the batteries and charge fully before use. If the unit does not work properly, contact an authorized service centre.

Caution:

• To avoid permanent damage, do not use a microwave oven to speed up the drying process.

Innovation, Science and Economic Development Canada Notices and other information

NOTICE:

This equipment meets the applicable Innovation, Science and Economic Development Canada Terminal Equipment Technical Specifications. This is confirmed by the registration number. The abbreviation, "IC:", before the registration number signifies that registration was performed based on a Declaration of Conformity indicating that Innovation, Science and Economic Development Canada technical specifications were met. It does not imply that Innovation, Science and Economic Development Canada approved the equipment.

Users should ensure, for their own protection, that the electrical ground connections of the power utility, telephone lines and internal metallic water pipe system, if present, are connected together. This precaution may be particularly important in rural areas.

NOTICE:

The Ringer Equivalence Number (REN) assigned to each terminal device provides an indication of the maximum number of terminals allowed to be connected to a telephone interface. The termination on an interface may consist of any combination of devices subject only to the requirement that the sum of the Ringer Equivalence Numbers of all the devices does not exceed 5. The Ringer Equivalence Number (REN) of this unit: (found on the bottom of the unit).

NOTICE:

This device complies with Innovation, Science and Economic Development Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Privacy of communications may not be ensured when using this telephone.

Some cordless telephones operate at frequencies that may cause interference to nearby TVs and VCRs. To minimize or prevent such interference, the base of the cordless telephone should not be placed near, or on top of, a TV or VCR. If interference is experienced, move the cordless telephone further away from the TV or VCR. This will often reduce, or eliminate, interference.

RF Exposure Warning:

- This product complies with IC radiation exposure limits set forth for an uncontrolled environment.
- To comply with IC RF exposure requirements, the base unit must be installed and operated 20 cm (8 inches) or more between product and all person's body.
- This product may not be collocated or operated in conjunction with any other antenna or transmitter.
- The handset may be carried and operated with only the specific provided belt clip.
 Other non-tested belt clips or similar body-worn accessories may not comply and must be avoided.

Warranty

Panasonic Canada Inc. 5770 Ambler Drive, Mississauga, Ontario L4W 2T3 PANASONIC PRODUCT - LIMITED WARRANTY

EXCHANGE PROGRAM

Panasonic Canada Inc. warrants this product to be free from defects in material and workmanship under normal use and for a period as stated below from the date of original purchase agrees to, at its option either (a) repair your product with new or refurbished parts, (b) replace it with a new or a refurbished equivalent value product, or (c) refund your purchase price. The decision to repair, replace or refund will be made by Panasonic Canada Inc.

Telephone Accessory / Product

One (1) year

This warranty is given only to the original purchaser, or the person for whom it was purchased as a gift, of a Panasonic brand product mentioned above sold by an authorized Panasonic dealer in Canada and purchased and used in Canada, which product was not sold "as is", and which product was delivered to you in new condition in the original packaging.

IN ORDER TO BE ELIGIBLE TO RECEIVE WARRANTY SERVICE HEREUNDER, A PURCHASE RECEIPT OR OTHER PROOF OF DATE OF ORIGINAL PURCHASE, SHOWING <u>AMOUNT PAID AND PLACE OF PURCHASE</u> IS REQUIRED

LIMITATIONS AND EXCLUSIONS

This warranty ONLY COVERS failures due to defects in materials or workmanship, and DOES NOT COVER normal wear and tear or cosmetic damage. The warranty ALSO DOES NOT COVER damages which are caused by products not supplied by Panasonic Canada Inc., or failures which result from accidents, misuse, abuse, neglect, mishandling, misapplication, alteration, faulty installation, set-up adjustments, misaglustment of consumer controls, improper maintenance, improper batteries, power line surge, lightning damage, modification, introduction of sand, humidity or liquids, commercial use such as hotel, office, restaurant, or other business or rental use of the product, or service by anyone other than a Authorized Servicer, or damage that is attributable to acts of God.

Rechargeable batteries are warranted for ninety (90) days from date of original purchase.

THIS EXPRESS, LIMITED WARRANTY IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESS OR IMPLIED, INCLUDING ANY IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. IN NO EVENT WILL PANASONIC CANADA INC. BE LIABLE FOR ANY SPECIAL, INDIRECT OR CONSEQUENTIAL DAMAGES RESULTING FROM THE USE OF THIS PRODUCT OR ARISING OUT OF ANY BEREACH OF ANY EXPRESS OR IMPLIED WARRANTY. (As examples, this warranty excludes damages for lost time, travel to and from the Authorized Servicer, loss of or damage to media or images, data or other memory or recorded content. This list of items is not exhaustive, but for illustration only.)

In certain instances, some jurisdictions do not allow the exclusion or limitation of incidental or consequential damages, or the exclusion of implied warranties, so the above limitations and exclusions may not be applicable. This warranty gives you specific legal rights and you may have other rights which vary depending on your province or territory.

CONTACT INFORMATION

For product information and operation assistance, please visit our Support page:

www.panasonic.ca/english/support

For defective product exchange within the warranty period, please contact the original dealer.

Index

3-way conference: 23, 28A Additional handset: 52

Alarm: 48

Answering calls: 21, 27 Answering system Call screening: 67

Erasing messages: 63, 64, 67 Greeting message: 62 Greeting only: 68

Listening to messages: 63, 67 New message alerting: 65

New message alerting: 65 Number of rings: 67 Recording time: 68 Remote access code: 66 Remote operation: 66 Ring count: 67

Toll saver: 67 Turning on/off: 62 Auto intercom: 30 Auto talk: 21, 44

B Baby monitor: 49 Battery: 10, 11

> Bluetooth wireless technology Cellular phone (Link to cell): 16 Headset: 60

Phonebook transfer: 57 Booster (Clarity booster): 22

C.WTG (Call Waiting Deluxe): 53

Call block: 31

One ring for blocked call: 33 Call Display service: 53

Call share: 23, 28
Call Waiting: 22, 27
Caller list: 54
Caller list edit: 55
Cellular calls: 20, 26
Cellular phone
Pairing: 16

Unpairing: 16 Chain dial: 37 CID (Call Display): 55 Conference calls: 23, 28

Control type: 12, 13 Customer support: 45, 47

D Date and time: 15 Dialing mode: 15

Direct command code: 39

Display

Contrast: 44, 47 Language: 15

E Eco mode: 11 Equalizer: 22

Error messages: 72

F Flash: 21, 27, 45 **G** Groups: 35

H Handset

Deregistration: 52 Name: 51 Registration: 52 Hold: 21, 27

Intercom: 30

K Key detector: 43, 46 Key tone: 44

L Landline calls: 20, 26 Line mode: 45

Link to cell

Alert settings for your DECT

phone: 59
Area code: 19
Auto connection: 18
Cellular line only mode: 18
Cellular line selection: 19
Connection: 18
Link to Cell cop: 58

Link to Cell app: 58
Ring as cell mode: 17
Select unit to ring: 17
Tout manage (SMS: Sh

Text message (SMS: Short Message Service) alert: *59*

Making calls: 20, 26 Missed calls: 53

Mute: 21, 27 Night mode: 49 Noise reduction: 22

P Pause: 21, 26 Phonebook: 34 PIN: 19

Power failure (power backup

operation): 24 Privacy mode: 45

R Redialing: 20, 21, 26 Ringer ID: 35 Ringer tone: 41, 43

Rotary/pulse service: 22, 28

S Speed dial: 37 SP-PHONE (Speakerphone): 20

T Talking Call Display: 53 Temporary tone dialing: 22, 28

Index

Time adjustment: 43
Transferring calls: 23, 28
Troubleshooting: 73
Visual Call Waiting: 22
VM (Voicemail): 69

Voice guidance language: 15 Voicemail: 68, 69

Volume

Volume Receiver: 20

Ringer (Base unit): 27, 46, 47 Ringer (Handset): 21, 41, 43

Speaker: 20, 26

W Wall mounting: 70

Notes

Notes

Notes

Ear	MOLIE	futuro	refere	200

We recommend keeping a record of the following information to assist with any repair under warranty.

Serial No.	Date of purchase	
(found on the bottom of the base unit)		
Name and address of dealer		

Attach your purchase receipt here.

Panasonic Canada Inc. 5770 Ambler Drive, Mississauga, Ontario L4W 2T3

© Panasonic Corporation 2016

Printed in Malaysia



PNQX6719YA TT0316MG1027